

# FMC003 Teltonika Data Sending Parameters ID

[Main Page](#) > [OBD Trackers](#) > [FMC003](#) > **FMC003 Teltonika Data Sending Parameters ID**

Document updated according firmware FMB.Ver.03.29.00 and newer.

FMB AVL ID's consist of these **parameters groups**:

□

## Contents

- [1 Permanent I/O elements](#)
- [2 Eventual I/O elements](#)
- [3 OBD elements](#)
- [4 OBD OEM elements](#)
- [5 BLE Sensors I/O elements](#)
- [6 CAN adapters elements](#)

## Permanent I/O elements

---

Property ID in AVL packet	Property Name	Bytes	Type	Value range		Multiplier	Units	Description	HW Support	Parameter Group
				Min	Max					
239	Ignition	1	Unsigned	0	1	-	-	0 - Ignition Off 1 - Ignition On	FMBXXX <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> 0 <a href="#">FMU125</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> 0 <a href="#">FMM80</a> A	Permanent I/O Elements

240	Movement	1	Unsigned	0	1	-	-	0 - Movement Off 1 - Movement On	<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMU125</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	Permanent I/O elements
80	Data Mode	1	Unsigned	0	5	-	-	0 - Home On Stop 1 - Home On Moving 2 - Roaming On Stop 3 - Roaming On Moving 4 - Unknown On Stop 5 - Unknown On Moving	<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	Permanent I/O Elements

21	GSM Signal	1	Unsigned	0	5	-	-	Value in range 1-5	<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> 0 <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> 0 <a href="#">FMM80</a> A <a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> 0 <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> 0 <a href="#">FMM80</a> A	Permanent I/O Elements
200	Sleep Mode	1	Unsigned	0	4	-	-	0 - No Sleep 1 - GPS Sleep 2 - Deep Sleep 3 - Online Sleep 4 - Ultra Sleep	<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> 0 <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> 0 <a href="#">FMM80</a> A	Permanent I/O Elements

69	GNSS Status	1	Unsigned	0	3	-	-	<ul style="list-style-type: none"> <li>0 - GNSS OFF</li> <li>1 - GNSS ON with fix</li> <li>2 - GNSS ON without fix</li> <li>3 - GNSS sleep</li> </ul>	FMBXXX <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> 0 <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> 0 <a href="#">FMM80</a> A FMBXXX <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> 0 <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> 0 <a href="#">FMM80</a> A	Permanent I/O Elements
181	GNSS PDOP	2	Unsigned	0	500	0.1		Coefficient, <a href="#">calculation formula</a>	FMBXXX <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> 0 <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> 0 <a href="#">FMM80</a> A	Permanent I/O Elements

182	GNSS HDOP	2	Unsigned	0	500	0.1	Coefficient, <a href="#">calculation formula</a>	FMBXXX FMB001 FMC001 FMB010 FMB002 FMB020 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMB140 FMB150 FMC150 FMM15 0 FMB900 FMB920 FMB962 FMB964 FM3001 FMB202 FMB204 FMB206 FMT100 MTB100 FMP100 MSP500 EMC800 FMM80 0 FMM80 A FMBXXX FMB001 FMC001 FMB010 FMB002 FMB020 FMB003 FMB110 FMB120 FMB122 FMB125 FMB130 FMB140 FMB150 FMC150 FMM15 0 FMU125 FMB900 FMB920 FMB962 FMB964 FM3001 FMB202 FMB204 FMB206 FMT100 MTB100 FMP100 MSP500 EMC800 FMM80 0 FMM80 A	Permanent I/O Elements
66	External Voltage	2	Unsigned	0	65535	0.001	V Voltage	0 FMU125 FMB900 FMB920 FMB962 FMB964 FM3001 FMB202 FMB204 FMB206 FMT100 MTB100 FMP100 MSP500 EMC800 FMM80 0 FMM80 A	Permanent I/O elements

										<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	Permanent I/O elements
24	Speed	2	Unsigned	0	350	-	km/h	GNSS Speed			
										<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	Permanent I/O elements
205	GSM Cell ID	2	Unsigned	0	65535	-	-	GSM base station ID			

206	GSM Area Code	2	Unsigned	0	65535	-	-	Location Area code (LAC), it depends on GSM operator. It provides unique number which assigned to a set of base GSM stations.	<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	Permanent I/O elements
67	Battery Voltage	2	Unsigned	0	65535	0.001	V	Voltage	<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	Permanent I/O elements

											<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMB140</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	Permanent I/O elements
68	Battery Current	2	Unsigned	0	65535	0.001	A	Current				
											<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	Permanent I/O elements
241	Active GSM Operator	4	Unsigned	0	42949 67295	-	-	Currently used GSM Operator code				



										<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	
199	Trip Odometer	4	Unsigned	0	21474 83647	-	m	Trip Odometer value		Permanent I/O elements	
										<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	
16	Total Odometer	4	Unsigned	0	21474 83647	-	-	Total Odometer value in meters		Permanent I/O elements	

											<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM150</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">MTB100</a>	
1	Digital Input 1	1	Unsigned	0	1	-	-	Logic: 0/1			Permanent I/O elements	
											<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM150</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">MTB100</a>	
9	Analog Input 1	2	Unsigned	0	65535	0.001	V	Voltage			Permanent I/O elements	
											<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM150</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">MTB100</a>	
											<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM150</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">MTB100</a>	
179	Digital Output 1	1	Unsigned	0	1	-	-	Logic: 0/1			Permanent I/O elements	
											<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM150</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">MTB100</a>	

										<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB140</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a> <a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB140</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	Permanent I/O elements
12	Fuel Used GPS	4	Unsigned	0	42949 67295	0.001	1	Fuel Used			
13	Fuel Rate GPS	2	Unsigned	0	32767	0.01	1/100k m	Average Fuel Use			

										<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> 0 <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> 0 <a href="#">FMM80</a> A FMBXXX <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> 0 <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> 0 <a href="#">FMM80</a> A	Permanent I/O elements
17	Axis X	2	Signed	-8000	8000	-	mG	X axis value			
18	Axis Y	2	Signed	-8000	8000	-	mG	Y axis value			

										<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> 0 <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> 0 <a href="#">FMM80</a> A <a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> 0 <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> 0 <a href="#">FMM80</a> A	Permanent I/O elements
19	Axis Z	2	Signed	-8000	8000	-	mG	Z axis value			
11	ICCID1	8	Unsigned	0	0xffffffff	-	-	Value of SIM ICCID, MSB			

10	SD Status	1	Unsigned	0	1	-	-	0 - not present 1 - present	<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">FMBXXX</a> <a href="#">FMB900</a> <a href="#">FMB910</a> <a href="#">FMB920</a> <a href="#">FMC920</a> <a href="#">FMM92</a> <a href="#">0</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB640</a> <a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB640</a> <a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB140</a>	Permanent I/O elements
2	Digital Input 2	1	Unsigned	0	1	-	-	Logic: 0/1	<a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB640</a> <a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB640</a> <a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB640</a> <a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB140</a>	Permanent I/O elements
3	Digital Input 3	1	Unsigned	0	1	-	-	Logic: 0/1	<a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB640</a> <a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB640</a> <a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB640</a> <a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB140</a>	Permanent I/O elements
6	Analog Input 2	2	Unsigned	0	65535	0.001	V	Voltage	<a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB140</a>	Permanent I/O elements

180	Digital Output 2	1	Unsigned	0	1	-	-	Logic 0/1	<a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a>	Permanent I/O elements
72	Dallas Temperature 1	4	Signed	-550	1150	0.1	°C	Degrees ( °C ), -55 - +115, if 850 - Sensor not ready if 2000 - Value read error if 3000 - Not connected if 4000 - ID failed if 5000 - same as 850	<a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a>	Permanent I/O elements
73	Dallas Temperature 2	4	Signed	-550	1150	0.1	°C	Degrees ( °C ), -55 - +115, if 850 - Sensor not ready if 2000 - Value read error if 3000 - Not connected if 4000 - ID failed if 5000 - same as 850	<a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a>	Permanent I/O elements
74	Dallas Temperature 3	4	Signed	-550	1150	0.1	°C	Degrees ( °C ), -55 - +115, if 850 - Sensor not ready if 2000 - Value read error if 3000 - Not connected if 4000 - ID failed if 5000 - same as 850	<a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a>	Permanent I/O elements

75	Dallas Temperature 4	4	Signed	-550	1150	0.1	°C	Degrees ( °C ), -55 - +115, if 850 - Sensor not ready if 2000 - Value read error if 3000 - Not connected if 4000 - ID failed if 5000 - same as 850	<a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a>	Permanent I/O elements
76	Dallas Temperature ID 1	8	Unsigned	0	0xffffffff	-	-	Dallas sensor ID	<a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a>	Permanent I/O elements
77	Dallas Temperature ID 2	8	Unsigned	0	0xffffffff	-	-	Dallas sensor ID	<a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a>	Permanent I/O elements
79	Dallas Temperature ID 3	8	Unsigned	0	0xffffffff	-	-	Dallas sensor ID	<a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a>	Permanent I/O elements



												<a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a> <a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM150</a>	
71	Dallas Temperature ID 4	8	Unsigned	0	0xffffffff	-	-	Dallas sensor ID				<a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM150</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a>	Permanent I/O elements
												<a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a> <a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM150</a>	
78	iButton	8	Unsigned	0	0xffffffff	-	-	iButton ID				<a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM150</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM130</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a>	Permanent I/O elements
												<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	
207	RFID	8	Unsigned	0	0xffffffff	-	-	RFID ID				<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	Permanent I/O elements
												<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	
201	LLS 1 Fuel Level	2	Signed	-4	32767	-	kvants or ltr	Fuel level measured by LLS sensor via RS232/RS485				<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	Permanent I/O elements
												<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	
202	LLS 1 Temperature	1	Signed	-128	127	-	°C	Fuel temperature measured by LLS via RS232/RS485				<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	Permanent I/O elements
												<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	
203	LLS 2 Fuel Level	2	Signed	-4	32767	-	kvants or ltr	Fuel level measured by LLS sensor via RS485				<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	Permanent I/O elements
												<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	
204	LLS 2 Temperature	1	Signed	-128	127	-	°C	Fuel temperature measured by LLS via RS485				<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	Permanent I/O elements
												<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	
210	LLS 3 Fuel Level	2	Unsigned	-4	32767	-	kvants or ltr	Fuel level measured by LLS sensor via RS485				<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	Permanent I/O elements
												<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	
211	LLS 3 Temperature	1	Signed	-128	127	-	°C	Fuel temperature measured by LLS via RS485				<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	Permanent I/O elements
												<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	

212	LLS 4 Fuel Level	2	Signed	-4	32767	-	kvants or ltr	Fuel level measured by LLS sensor via RS485	<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	Permanent I/O elements
213	LLS 4 Temperature	1	Signed	-128	127	-	°C	Fuel temperature measured by LLS via RS485	<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	Permanent I/O elements
214	LLS 5 Fuel Level	2	Signed	-4	32767	-	kvants or ltr	Fuel level measured by LLS sensor via RS485	<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	Permanent I/O elements
215	LLS 5 Temperature	1	Signed	-128	127	-	°C	Fuel temperature measured by LLS via RS485	<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	Permanent I/O elements
15	Eco Score	2	Unsigned	0	65535	0.01	-	Average amount of events on some distance	FMBXXX <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a> 5 <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM130</a> 0 <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM150</a> 0 <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMC800</a> <a href="#">FMM80</a> 0 <a href="#">FMM80</a> A FMBXXX <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM150</a> 0	Permanent I/O elements
113	Battery Level	1	Unsigned	0	100	-	%	Battery capacity level	0 <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMC800</a> <a href="#">FMM80</a> 0 <a href="#">FMM80</a> A	Permanent I/O elements

											<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">FMP100</a> <a href="#">FMC001</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM00</a> <a href="#">1</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a> <a href="#">FMC880</a> <a href="#">FMM88</a> <a href="#">0</a> <a href="#">FMC250</a>	
238	User ID	8	Unsigned	0	0xffffffff	-	-	MAC address of NMEA receiver device connected via Bluetooth			<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">FMP100</a> <a href="#">FMC001</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM00</a> <a href="#">1</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a> <a href="#">FMC880</a> <a href="#">FMM88</a> <a href="#">0</a> <a href="#">FMC250</a>	Permanent I/O elements
											<a href="#">FMBXXX</a> <a href="#">FM3001</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMC150</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMC001</a> <a href="#">FMM00</a> <a href="#">1</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMC880</a> <a href="#">FMM88</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	
237	Network Type	1	Unsigned	0	1	-	-	0 - 3G 1 - GSM 2 - 4G 3 - LTE CAT M1 4 - LTE CAT NB1 99 - Unknown			<a href="#">FMBXXX</a> <a href="#">FM3001</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMC150</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMC001</a> <a href="#">FMM00</a> <a href="#">1</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMC880</a> <a href="#">FMM88</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	Permanent I/O elements
											<a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a>	
4	Pulse Counter Din1	4	Unsigned	0	4294967295	-	-	Counts pulses, count is reset when records are saved			<a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a>	Permanent I/O elements
											<a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a>	
5	Pulse Counter Din2	4	Unsigned	0	4294967295	-	-	Counts pulses, count is reset when records are saved			<a href="#">FMBXXX</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a>	Permanent I/O elements

										<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a> <a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a>	Permanent I/O elements
263	BT Status	1	Unsigned	0	4	-	-	0 - BT is disabled 1 - BT Enabled, not device connected 2 - Device connected, BTv3 Only 3 - Device connected, BLE only 4 - Device connected, BLE + BT			
264	Barcode ID	Variable	ASCII	0	32	-	-	Barcode ID			

										<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM130</a>	
303	Instant Movement	1	Unsigned	0	1	-	-	Logic: 0/1 returns movement value		<a href="#">FMM130</a> <a href="#">FMM130</a> <a href="#">FMM130</a> <a href="#">FMM130</a>	Permanent I/O elements
327	UL202-02 Sensor Fuel level	2	Signed	-150	32767	0.1	mm	UL202-02 Sensor Fuel level		<a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM150</a> <a href="#">FMM150</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	Permanent I/O elements
483	UL202-02 Sensor Status	1	Unsigned	0	255	-	-	UL202-02 sensor status codes		<a href="#">FMB125</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a>	Permanent I/O elements
380	Digital output 3	1	Unsigned	0	1	-	-	Logic: 0/1		<a href="#">FMM125</a> <a href="#">FMM125</a> <a href="#">FMM125</a> <a href="#">FMM125</a>	Permanent I/O elements
381	Ground Sense	1	Unsigned	0	1	-	-	Logic: 0/1		<a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM130</a> <a href="#">FMM130</a> <a href="#">FMM130</a>	Permanent I/O elements

										<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB002</a> <a href="#">FMB020</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM15</a>		
387	ISO6709 Coordinates	34	HEX	0	0x7fffff ffffff	-	-	-	-	ISO6709 Coordinates Latitude, Longitude (in Degrees, Minutes and Seconds) and Altitude: IO value format: ±DDMMSS.SSSS±DDMMSS.SSSS±AAA.AAA/	<a href="#">0</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB910</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMP100</a> <a href="#">FMB140</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	Permanent I/O elements
										<a href="#">FMBXXX</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC001</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM00</a> <a href="#">1</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>		
636	UMTS/LTE Cell ID	4	Unsigned	0	0xFFFF FFFF	-	-	-	-		<a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMC150</a> <a href="#">FMM15</a> <a href="#">0</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	Permanent I/O elements
403	Driver Name	35	Unsigned	-	-	-	-	-	-	Driver name extracted from card, displayed without delimiters (\$ signs) None - 0 B.1 license type - 1 B.2 license type - 2 B.3 license type - 3 B.4 license type - 4 T.1 license type - 5 T.2 license type - 6 T.3 license type - 7 T.4 license type - 8	<a href="#">FMBXXX</a> <a href="#">FMU126</a>	Permanent I/O elements
404	Driver card license type	1	Unsigned	0	8	-	-	-	-		<a href="#">FMBXXX</a> <a href="#">FMU126</a>	Permanent I/O elements
405	Driver Gender	1	Unsigned	0	2	-	-	-	-	None - 0 Male - 1 Female - 2	<a href="#">FMBXXX</a> <a href="#">FMU126</a>	Permanent I/O elements
406	Driver Card ID	4	Unsigned	0	42949 67295	-	-	-	-	None - 0 Male - 1 Female - 2	<a href="#">FMBXXX</a> <a href="#">FMU126</a>	Permanent I/O elements
407	Driver card expiration date	1	Unsigned	0	9999	-	-	-	-		<a href="#">FMBXXX</a> <a href="#">FMU126</a>	Permanent I/O elements
408	Driver Card place of issue	4	Unsigned	0	65535	-	-	-	-	Extracted from card	<a href="#">FMBXXX</a> <a href="#">FMU126</a>	Permanent I/O Elements
409	Driver Status Event	1	Unsigned	0	2	-	-	-	-	Registered - 0 Deregistered - 1 Swapping - 2	<a href="#">FMBXXX</a> <a href="#">FMU126</a>	Permanent I/O elements

329	AIN Speed	2	Unsigned	0	65535	-	-		<a href="#">MSP500</a>	Permanent I/O elements
500	MSP500 vendor name	40	ASCII	0	40	-	-	Name of the integrator who installed the device	<a href="#">MSP500</a>	Permanent I/O elements
501	MSP500 vehicle number	40	ASCII	0	40	-	-	Vehicle number on which the device is installed	<a href="#">MSP500</a>	Permanent I/O elements
502	MSP500 speed sensor	1	unsigned	0	1	-	-	Status of the speed sensor	<a href="#">MSP500</a>	Permanent I/O elements
637	Wake Reason	1	Unsigned	0	1	-	-	True if device was woken by RTC alarm	<a href="#">FMB965</a>	Permanent I/O elements
									<a href="#">FMBXXX</a>	
									<a href="#">[Expand]</a>	
									<a href="#">FMB001</a>	
									<a href="#">FMB010</a>	
									<a href="#">FMB100</a>	
									<a href="#">FMB110</a>	
									<a href="#">FMB120</a>	
									<a href="#">FMB122</a>	
									<a href="#">FMB125</a>	
									<a href="#">FMB130</a>	
									<a href="#">FMB900</a>	
									<a href="#">FMB920</a>	
									<a href="#">FMB962</a>	
									<a href="#">FMB964</a>	
									<a href="#">FM3001</a>	
									<a href="#">FM3010</a>	
									<a href="#">FMB202</a>	
									<a href="#">FMB204</a>	
									<a href="#">FMB206</a>	
									<a href="#">FMB207</a>	
									<a href="#">FMT100</a>	
									<a href="#">MTB100</a>	
10800	EYE Temperature 1	2	Signed	-32768	32767	0.01	°C	Temperature measured by EYE Sensor 1	<a href="#">TMT250</a>	Permanent I/O elements
									<a href="#">GH5200</a>	
									<a href="#">FMB140</a>	
									<a href="#">FMB020</a>	
									<a href="#">FMB002</a>	
									<a href="#">FMB003</a>	
									<a href="#">FMU120</a>	
									<a href="#">FMU122</a>	
									<a href="#">FMU125</a>	
									<a href="#">FMU126</a>	
									<a href="#">FMU130</a>	
									<a href="#">FMC120</a>	
									<a href="#">FMC122</a>	
									<a href="#">FMC125</a>	
									<a href="#">FMC130</a>	
									<a href="#">FMM12</a>	
									<a href="#">5</a>	
									<a href="#">FMM13</a>	
									<a href="#">0</a>	
									<a href="#">FMC001</a>	
									<a href="#">FMM00</a>	
									<a href="#">1</a>	
									<a href="#">TFT100</a>	
									<a href="#">FMB910</a>	

10801 EYE Temperature 2 2 Signed -32768 32767 0.01 °C Temperature measured by EYE Sensor 2

[FMBXXX](#)  
[\[Expand\]](#)  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
[5](#)  
[FMM13](#)  
[0](#)  
[FMC001](#)  
[FMM00](#)  
[1](#)  
[TFT100](#)  
[FMB910](#)

Permanent I/O  
elements



10802 EYE Temperature 3 2 Signed -32768 32767 0.01 °C Temperature measured by EYE Sensor 3

[FMBXXX](#)  
[\[Expand\]](#)  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
[5](#)  
[FMM13](#)  
[0](#)  
[FMC001](#)  
[FMM00](#)  
[1](#)  
[TFT100](#)  
[FMB910](#)

Permanent I/O elements

10803 EYE Temperature 4 2 Signed -32768 32767 0.01 °C Temperature measured by EYE Sensor 4

[FMBXXX](#)  
[\[Expand\]](#)  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
[5](#)  
[FMM13](#)  
[0](#)  
[FMC001](#)  
[FMM00](#)  
[1](#)  
[TFT100](#)  
[FMB910](#)

Permanent I/O  
elements

10804 EYE Humidity 1 1 Unsigned 0 100 - % Humidity measured by EYE Sensor 1

[FMBXXX](#)  
[\[Expand\]](#)  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
[5](#)  
[FMM13](#)  
[0](#)  
[FMC001](#)  
[FMM00](#)  
[1](#)  
[TFT100](#)  
[FMB910](#)

Permanent I/O elements

10805 EYE Humidity 2 1 Unsigned 0 100 - % Humidity measured by EYE Sensor 2

- [FMBXXX](#)
- [\[Expand\]](#)
- [FMB001](#)
- [FMB010](#)
- [FMB100](#)
- [FMB110](#)
- [FMB120](#)
- [FMB122](#)
- [FMB125](#)
- [FMB130](#)
- [FMB900](#)
- [FMB920](#)
- [FMB962](#)
- [FMB964](#)
- [FM3001](#)
- [FM3010](#)
- [FMB202](#)
- [FMB204](#)
- [FMB206](#)
- [FMB207](#)
- [FMT100](#)
- [MTB100](#)
- [TMT250](#)
- [GH5200](#)
- [FMB140](#)
- [FMB020](#)
- [FMB002](#)
- [FMB003](#)
- [FMU120](#)
- [FMU122](#)
- [FMU125](#)
- [FMU126](#)
- [FMU130](#)
- [FMC120](#)
- [FMC122](#)
- [FMC125](#)
- [FMC130](#)
- [FMM12](#)
- [5](#)
- [FMM13](#)
- [0](#)
- [FMC001](#)
- [FMM00](#)
- [1](#)
- [TFT100](#)
- [FMB910](#)

Permanent I/O elements

10806 EYE Humidity 3 1 Unsigned 0 100 - % Humidity measured by EYE Sensor 3

[FMBXXX](#)  
[\[Expand\]](#)  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
[5](#)  
[FMM13](#)  
[0](#)  
[FMC001](#)  
[FMM00](#)  
[1](#)  
[TFT100](#)  
[FMB910](#)

Permanent I/O elements

10807 EYE Humidity 4 1 Unsigned 0 100 - % Humidity measured by EYE Sensor 4

- [FMBXXX](#)
- [\[Expand\]](#)
- [FMB001](#)
- [FMB010](#)
- [FMB100](#)
- [FMB110](#)
- [FMB120](#)
- [FMB122](#)
- [FMB125](#)
- [FMB130](#)
- [FMB900](#)
- [FMB920](#)
- [FMB962](#)
- [FMB964](#)
- [FM3001](#)
- [FM3010](#)
- [FMB202](#)
- [FMB204](#)
- [FMB206](#)
- [FMB207](#)
- [FMT100](#)
- [MTB100](#)
- [TMT250](#)
- [GH5200](#)
- [FMB140](#)
- [FMB020](#)
- [FMB002](#)
- [FMB003](#)
- [FMU120](#)
- [FMU122](#)
- [FMU125](#)
- [FMU126](#)
- [FMU130](#)
- [FMC120](#)
- [FMC122](#)
- [FMC125](#)
- [FMC130](#)
- [FMM12](#)
- [5](#)
- [FMM13](#)
- [0](#)
- [FMC001](#)
- [FMM00](#)
- [1](#)
- [TFT100](#)
- [FMB910](#)

Permanent I/O elements

FMBXXX  
[Expand]  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
5  
[FMM13](#)  
0  
[FMC001](#)  
[FMM00](#)  
1  
[TFT100](#)  
[FMB910](#)

10808	EYE Magnet 1	1	Unsign ed	0	1	-	-	Magnet measured by EYE Sensor by EYE Sensor 1	Permanent I/O elements
-------	--------------	---	--------------	---	---	---	---	-----------------------------------------------	---------------------------

											<a href="#">FMBXXX</a> <a href="#">[Expand]</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB100</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FM3010</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB207</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">TMT250</a> <a href="#">GH5200</a> <a href="#">FMB140</a> <a href="#">FMB020</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMU120</a> <a href="#">FMU122</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC120</a> <a href="#">FMC122</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM12</a> 5 <a href="#">FMM13</a> 0 <a href="#">FMC001</a> <a href="#">FMM00</a> 1 <a href="#">TFT100</a> <a href="#">FMB910</a>
10809	EYE Magnet 2	1	Unsign ed	0	1	-	-	Magnet measured by EYE Sensor by EYE Sensor 2			Permanent I/O elements



10810	EYE Magnet 3	1	Unsigned	0	1	-	-	Magnet measured by EYE Sensor by EYE Sensor 3	<a href="#">FMBXXX</a> <a href="#">[Expand]</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB100</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FM3010</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB207</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">TMT250</a> <a href="#">GH5200</a> <a href="#">FMB140</a> <a href="#">FMB020</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMU120</a> <a href="#">FMU122</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC120</a> <a href="#">FMC122</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMC001</a> <a href="#">FMM00</a> <a href="#">1</a> <a href="#">TFT100</a> <a href="#">FMB910</a>	Permanent I/O elements
-------	--------------	---	----------	---	---	---	---	-----------------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	------------------------

FMBXXX  
[Expand]  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
5  
[FMM13](#)  
0  
[FMC001](#)  
[FMM00](#)  
1  
[TFT100](#)  
[FMB910](#)

10811      EYE Magnet 4      1      Unsigned      0      1      -      -      Magnet measured by EYE Sensor by EYE Sensor 4      Permanent I/O elements

FMBXXX  
[Expand]  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
5  
[FMM13](#)  
0  
[FMC001](#)  
[FMM00](#)  
1  
[TFT100](#)  
[FMB910](#)

10812 EYE Movement 1 2 Unsigned 0 0xFFFF - - Movement state measure by EYE Sensor 1

Permanent I/O elements

10813	EYE Movement 2	2	Unsign ed	0	0xFFFF F	-	-	Movement state measure by EYE Sensor 2	<a href="#">FMBXXX</a> <a href="#">[Expand]</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB100</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FM3010</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB207</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">TMT250</a> <a href="#">GH5200</a> <a href="#">FMB140</a> <a href="#">FMB020</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMU120</a> <a href="#">FMU122</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC120</a> <a href="#">FMC122</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMC001</a> <a href="#">FMM00</a> <a href="#">1</a> <a href="#">TFT100</a> <a href="#">FMB910</a>	Permanent I/O elements
-------	----------------	---	--------------	---	-------------	---	---	----------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	---------------------------

10814	EYE Movement 3	2	Unsign ed	0	0xFFFF F	-	-	Movement state measure by EYE Sensor 3	<a href="#">FMBXXX</a> <a href="#">[Expand]</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB100</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FM3010</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB207</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">TMT250</a> <a href="#">GH5200</a> <a href="#">FMB140</a> <a href="#">FMB020</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMU120</a> <a href="#">FMU122</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC120</a> <a href="#">FMC122</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMC001</a> <a href="#">FMM00</a> <a href="#">1</a> <a href="#">TFT100</a> <a href="#">FMB910</a>	Permanent I/O elements
-------	----------------	---	--------------	---	-------------	---	---	----------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	---------------------------

10815	EYE Movement 4	2	Unsign ed	0	0xFFFF F	-	-	Movement state measure by EYE Sensor 4	<a href="#">FMBXXX</a> <a href="#">[Expand]</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB100</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FM3010</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB207</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">TMT250</a> <a href="#">GH5200</a> <a href="#">FMB140</a> <a href="#">FMB020</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMU120</a> <a href="#">FMU122</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC120</a> <a href="#">FMC122</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMC001</a> <a href="#">FMM00</a> <a href="#">1</a> <a href="#">TFT100</a> <a href="#">FMB910</a>	Permanent I/O elements
-------	----------------	---	--------------	---	-------------	---	---	----------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	---------------------------

10816 EYE Pitch 1 1 Signed -90 90 - - Pitch angle measured by EYE Sensor 1

- [FMBXXX](#)
- [\[Expand\]](#)
- [FMB001](#)
- [FMB010](#)
- [FMB100](#)
- [FMB110](#)
- [FMB120](#)
- [FMB122](#)
- [FMB125](#)
- [FMB130](#)
- [FMB900](#)
- [FMB920](#)
- [FMB962](#)
- [FMB964](#)
- [FM3001](#)
- [FM3010](#)
- [FMB202](#)
- [FMB204](#)
- [FMB206](#)
- [FMB207](#)
- [FMT100](#)
- [MTB100](#)
- [TMT250](#)
- [GH5200](#)
- [FMB140](#)
- [FMB020](#)
- [FMB002](#)
- [FMB003](#)
- [FMU120](#)
- [FMU122](#)
- [FMU125](#)
- [FMU126](#)
- [FMU130](#)
- [FMC120](#)
- [FMC122](#)
- [FMC125](#)
- [FMC130](#)
- [FMM12](#)
- [5](#)
- [FMM13](#)
- [0](#)
- [FMC001](#)
- [FMM00](#)
- [1](#)
- [TFT100](#)
- [FMB910](#)

Permanent I/O elements

10817	EYE Pitch 2	1	Signed	-90	90	-	-	Pitch angle measured by EYE Sensor 2	<a href="#">FMBXXX</a> <a href="#">[Expand]</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB100</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FM3010</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB207</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">TMT250</a> <a href="#">GH5200</a> <a href="#">FMB140</a> <a href="#">FMB020</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMU120</a> <a href="#">FMU122</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC120</a> <a href="#">FMC122</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMC001</a> <a href="#">FMM00</a> <a href="#">1</a> <a href="#">TFT100</a> <a href="#">FMB910</a>	Permanent I/O elements
-------	-------------	---	--------	-----	----	---	---	--------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	------------------------



10818 EYE Pitch 3 1 Signed -90 90 - - Pitch angle measured by EYE Sensor 3

FMBXXX  
[Expand]  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
5  
[FMM13](#)  
0  
[FMC001](#)  
[FMM00](#)  
1  
[TFT100](#)  
[FMB910](#)

Permanent I/O  
elements

10819 EYE Pitch 4 1 Signed -90 90 - - Pitch angle measured by EYE Sensor 4

[FMBXXX](#)  
[\[Expand\]](#)  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
[5](#)  
[FMM13](#)  
[0](#)  
[FMC001](#)  
[FMM00](#)  
[1](#)  
[TFT100](#)  
[FMB910](#)

Permanent I/O  
elements

10820	EYE Low Battery 1	1	Unsigned	0	1	-	-	Low Battery indication for EYE Sensor 1	<a href="#">FMBXXX</a> <a href="#">[Expand]</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB100</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FM3010</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB207</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">TMT250</a> <a href="#">GH5200</a> <a href="#">FMB140</a> <a href="#">FMB020</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMU120</a> <a href="#">FMU122</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC120</a> <a href="#">FMC122</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMC001</a> <a href="#">FMM00</a> <a href="#">1</a> <a href="#">TFT100</a> <a href="#">FMB910</a>	Permanent I/O elements
-------	-------------------	---	----------	---	---	---	---	-----------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	------------------------

10821 EYE Low Battery 2 1 Unsigned 0 1 - - Low Battery indication for EYE Sensor 2

FMBXXX  
[\[Expand\]](#)  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
 5  
[FMM13](#)  
 0  
[FMC001](#)  
[FMM00](#)  
 1  
[TFT100](#)  
[FMB910](#)

Permanent I/O elements

10822	EYE Low Battery 3	1	Unsigned	0	1	-	-	Low Battery indication for EYE Sensor 3
-------	-------------------	---	----------	---	---	---	---	-----------------------------------------

[FMBXXX](#)  
[\[Expand\]](#)  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
5  
[FMM13](#)  
0  
[FMC001](#)  
[FMM00](#)  
1  
[TFT100](#)  
[FMB910](#)

Permanent I/O elements

FMBXXX

[Expand]

[FMB001](#)

[FMB010](#)

[FMB100](#)

[FMB110](#)

[FMB120](#)

[FMB122](#)

[FMB125](#)

[FMB130](#)

[FMB900](#)

[FMB920](#)

[FMB962](#)

[FMB964](#)

[FM3001](#)

[FM3010](#)

[FMB202](#)

[FMB204](#)

[FMB206](#)

[FMB207](#)

[FMT100](#)

[MTB100](#)

[TMT250](#)

[GH5200](#)

[FMB140](#)

[FMB020](#)

[FMB002](#)

[FMB003](#)

[FMU120](#)

[FMU122](#)

[FMU125](#)

[FMU126](#)

[FMU130](#)

[FMC120](#)

[FMC122](#)

[FMC125](#)

[FMC130](#)

[FMM12](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

[FMM13](#)

10823 EYE Low Battery 4 1 Unsigned 0 1 - - Low Battery indication for EYE Sensor 4

Permanent I/O elements

10824 EYE Battery Voltage 1 1 Unsigned 0 0xFF - - Battery Voltage of EYE Sensor 1

[FMBXXX](#)  
[\[Expand\]](#)  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
5  
[FMM13](#)  
0  
[FMC001](#)  
[FMM00](#)  
1  
[TFT100](#)  
[FMB910](#)

Permanent I/O elements

10825 EYE Battery Voltage 2 1 Unsigned 0 0xFF - - Battery Voltage of EYE Sensor 2

[FMBXXX](#)  
[\[Expand\]](#)  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
5  
[FMM13](#)  
0  
[FMC001](#)  
[FMM00](#)  
1  
[TFT100](#)  
[FMB910](#)

Permanent I/O elements



10826 EYE Battery Voltage 3 1 Unsigned 0 0xFF - - Battery Voltage of EYE Sensor 3

- [FMBXXX](#)
- [\[Expand\]](#)
- [FMB001](#)
- [FMB010](#)
- [FMB100](#)
- [FMB110](#)
- [FMB120](#)
- [FMB122](#)
- [FMB125](#)
- [FMB130](#)
- [FMB900](#)
- [FMB920](#)
- [FMB962](#)
- [FMB964](#)
- [FM3001](#)
- [FM3010](#)
- [FMB202](#)
- [FMB204](#)
- [FMB206](#)
- [FMB207](#)
- [FMT100](#)
- [MTB100](#)
- [TMT250](#)
- [GH5200](#)
- [FMB140](#)
- [FMB020](#)
- [FMB002](#)
- [FMB003](#)
- [FMU120](#)
- [FMU122](#)
- [FMU125](#)
- [FMU126](#)
- [FMU130](#)
- [FMC120](#)
- [FMC122](#)
- [FMC125](#)
- [FMC130](#)
- [FMM12](#)
- [5](#)
- [FMM13](#)
- [0](#)
- [FMC001](#)
- [FMM00](#)
- [1](#)
- [TFT100](#)
- [FMB910](#)

Permanent I/O elements

10827 EYE Battery Voltage 4 1 Unsigned 0 0xFF - - Battery Voltage of EYE Sensor 4

[FMBXXX](#)  
[\[Expand\]](#)  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
5  
[FMM13](#)  
0  
[FMC001](#)  
[FMM00](#)  
1  
[TFT100](#)  
[FMB910](#)

Permanent I/O elements

10832 EYE Roll 1 2 Signed -180 180 - - Roll angle measured by EYE Sensor 1

- [FMBXXX](#)
- [\[Expand\]](#)
- [FMB001](#)
- [FMB010](#)
- [FMB100](#)
- [FMB110](#)
- [FMB120](#)
- [FMB122](#)
- [FMB125](#)
- [FMB130](#)
- [FMB900](#)
- [FMB920](#)
- [FMB962](#)
- [FMB964](#)
- [FM3001](#)
- [FM3010](#)
- [FMB202](#)
- [FMB204](#)
- [FMB206](#)
- [FMB207](#)
- [FMT100](#)
- [MTB100](#)
- [TMT250](#)
- [GH5200](#)
- [FMB140](#)
- [FMB020](#)
- [FMB002](#)
- [FMB003](#)
- [FMU120](#)
- [FMU122](#)
- [FMU125](#)
- [FMU126](#)
- [FMU130](#)
- [FMC120](#)
- [FMC122](#)
- [FMC125](#)
- [FMC130](#)
- [FMM12](#)
- [5](#)
- [FMM13](#)
- [0](#)
- [FMC001](#)
- [FMM00](#)
- [1](#)
- [TFT100](#)
- [FMB910](#)

Permanent I/O elements

10833 EYE Roll 2 2 Signed -180 180 - - Roll angle measured by EYE Sensor 2

[FMBXXX](#)  
[\[Expand\]](#)  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
[5](#)  
[FMM13](#)  
[0](#)  
[FMC001](#)  
[FMM00](#)  
[1](#)  
[TFT100](#)  
[FMB910](#)

Permanent I/O  
elements

10834 EYE Roll 3 2 Signed -180 180 - - Roll angle measured by EYE Sensor 3

FMBXXX  
[Expand]  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
5  
[FMM13](#)  
0  
[FMC001](#)  
[FMM00](#)  
1  
[TFT100](#)  
[FMB910](#)

Permanent I/O  
elements

10835 EYE Roll 4 2 Signed -180 180 - - Roll angle measured by EYE Sensor 4

- [FMBXXX](#)
- [\[Expand\]](#)
- [FMB001](#)
- [FMB010](#)
- [FMB100](#)
- [FMB110](#)
- [FMB120](#)
- [FMB122](#)
- [FMB125](#)
- [FMB130](#)
- [FMB900](#)
- [FMB920](#)
- [FMB962](#)
- [FMB964](#)
- [FM3001](#)
- [FM3010](#)
- [FMB202](#)
- [FMB204](#)
- [FMB206](#)
- [FMB207](#)
- [FMT100](#)
- [MTB100](#)
- [TMT250](#)
- [GH5200](#)
- [FMB140](#)
- [FMB020](#)
- [FMB002](#)
- [FMB003](#)
- [FMU120](#)
- [FMU122](#)
- [FMU125](#)
- [FMU126](#)
- [FMU130](#)
- [FMC120](#)
- [FMC122](#)
- [FMC125](#)
- [FMC130](#)
- [FMM12](#)
- [5](#)
- [FMM13](#)
- [0](#)
- [FMC001](#)
- [FMM00](#)
- [1](#)
- [TFT100](#)
- [FMB910](#)

Permanent I/O elements

FMBXXX  
[Expand]  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
5  
[FMM13](#)  
0  
[FMC001](#)  
[FMM00](#)  
1  
[TFT100](#)  
[FMB910](#)

10836 EYE Movement count 2 Unsigned 0 32767 - - Movement count measure by EYE Sensor 1

Permanent I/O elements

FMBXXX  
[Expand]  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
5  
[FMM13](#)  
0  
[FMC001](#)  
[FMM00](#)  
1  
[TFT100](#)  
[FMB910](#)

10837 EYE Movement count 2 Unsigned 0 32767 - - Movement count measure by EYE Sensor 2

Permanent I/O elements



10838	EYE Movement count 3	2	Unsign ed	0	32767	-	-	Movement count measure by EYE Sensor 3	<a href="#">FMBXXX</a> <a href="#">[Expand]</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB100</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FM3010</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB207</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">TMT250</a> <a href="#">GH5200</a> <a href="#">FMB140</a> <a href="#">FMB020</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMU120</a> <a href="#">FMU122</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC120</a> <a href="#">FMC122</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMC001</a> <a href="#">FMM00</a> <a href="#">1</a> <a href="#">TFT100</a> <a href="#">FMB910</a>	Permanent I/O elements
-------	-------------------------	---	--------------	---	-------	---	---	----------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	---------------------------

FMBXXX  
[Expand]  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[MTT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
5  
[FMM13](#)  
0  
[FMC001](#)  
[FMM00](#)  
1  
[TFT100](#)  
[FMB910](#)

10839 EYE Movement count 2 Unsign 0 32767 - - Movement count measure by EYE Sensor 4

Permanent I/O elements

10840	EYE Magnet count 1	2	Unsigned	0	65535	-	-	Magnet trigger count measure by EYE Sensor 1	<a href="#">FMBXXX</a> <a href="#">[Expand]</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB100</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FM3010</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB207</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">TMT250</a> <a href="#">GH5200</a> <a href="#">FMB140</a> <a href="#">FMB020</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMU120</a> <a href="#">FMU122</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC120</a> <a href="#">FMC122</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMC001</a> <a href="#">FMM00</a> <a href="#">1</a> <a href="#">TFT100</a> <a href="#">FMB910</a>	Permanent I/O elements
-------	--------------------	---	----------	---	-------	---	---	----------------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	------------------------

- [FMBXXX](#)
- [\[Expand\]](#)
- [FMB001](#)
- [FMB010](#)
- [FMB100](#)
- [FMB110](#)
- [FMB120](#)
- [FMB122](#)
- [FMB125](#)
- [FMB130](#)
- [FMB900](#)
- [FMB920](#)
- [FMB962](#)
- [FMB964](#)
- [FM3001](#)
- [FM3010](#)
- [FMB202](#)
- [FMB204](#)
- [FMB206](#)
- [FMB207](#)
- [FMT100](#)
- [MTB100](#)
- [TMT250](#)
- [GH5200](#)
- [FMB140](#)
- [FMB020](#)
- [FMB002](#)
- [FMB003](#)
- [FMU120](#)
- [FMU122](#)
- [FMU125](#)
- [FMU126](#)
- [FMU130](#)
- [FMC120](#)
- [FMC122](#)
- [FMC125](#)
- [FMC130](#)
- [FMM12](#)
- 5
- [FMM13](#)
- 0
- [FMC001](#)
- [FMM00](#)
- 1
- [TFT100](#)
- [FMB910](#)

10841 EYE Magnet count 2 2 Unsigned 0 65535 - - Magnet trigger count measure by EYE Sensor 2

Permanent I/O elements

[FMBXXX](#)  
[\[Expand\]](#)  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
[5](#)  
[FMM13](#)  
[0](#)  
[FMC001](#)  
[FMM00](#)  
[1](#)  
[TFT100](#)  
[FMB910](#)

10842	EYE Magnet count 3	2	Unsign ed	0	65535	-	-	Magnet trigger count measure by EYE Sensor 3
-------	--------------------	---	--------------	---	-------	---	---	----------------------------------------------

Permanent I/O  
elements

FMBXXX

[\[Expand\]](#)

[FMB001](#)

[FMB010](#)

[FMB100](#)

[FMB110](#)

[FMB120](#)

[FMB122](#)

[FMB125](#)

[FMB130](#)

[FMB900](#)

[FMB920](#)

[FMB962](#)

[FMB964](#)

[FM3001](#)

[FM3010](#)

[FMB202](#)

[FMB204](#)

[FMB206](#)

[FMB207](#)

[FMT100](#)

[MTB100](#)

[TMT250](#)

[GH5200](#)

[FMB140](#)

[FMB020](#)

[FMB002](#)

[FMB003](#)

[FMU120](#)

[FMU122](#)

[FMU125](#)

[FMU126](#)

[FMU130](#)

[FMC120](#)

[FMC122](#)

[FMC125](#)

[FMC130](#)

[FMM12](#)

[5](#)

[FMM13](#)

[0](#)

[FMC001](#)

[FMM00](#)

[1](#)

[TFT100](#)

[FMB910](#)

10843 EYE Magnet count 4 2 Unsigned 0 65535 - - Magnet trigger count measure by EYE Sensor 4

Permanent I/O elements

[FMBXXX](#)  
[\[Expand\]](#)  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMB208](#)  
[FMB209](#)  
[FMT100](#)  
[MTB100](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
[5](#)  
[FMM13](#)  
[0](#)  
[FMC001](#)  
[FMM00](#)  
[1](#)  
[FMB910](#)  
[FMC800](#)  
[FMM80](#)  
[0](#)  
[FMC880](#)  
[FMM88](#)  
[0](#)  
[FMM80](#)  
[A](#)

383 AXL Calibration Status 1 Unsigned 0 3 - - Shows calibration status: 0- no calibration, 1- calibrated, 2- not configured, 3- fully calibrated

Permanent I/O elements

451	BLE RFID #1	8	HEX	0	0xffffffff ffffffff	-	-	BLE NBL-T RFID ID for Connentionless mode #1 slot	<a href="#">FMBXXX</a> <a href="#">[Expand]</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB100</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FM3010</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB207</a> <a href="#">FMB208</a> <a href="#">FMB209</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">TMT250</a> <a href="#">GH5200</a> <a href="#">FMB140</a> <a href="#">FMB020</a> <a href="#">FMB002</a> <a href="#">FMB003</a> Permanent I/O <a href="#">FMU120</a> elements <a href="#">FMU122</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC120</a> <a href="#">FMC122</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM12</a> 5 <a href="#">FMM13</a> 0 <a href="#">FMC001</a> <a href="#">FMM00</a> 1 <a href="#">TFT100</a> <a href="#">FMB910</a> <a href="#">FMP100</a> <a href="#">FMP1M</a> 1 <a href="#">MSP500</a> <a href="#">EMC800</a> <a href="#">FMM80</a> 0 <a href="#">FMC880</a> <a href="#">FMM88</a> 0 <a href="#">FMM80</a> A
-----	-------------	---	-----	---	------------------------	---	---	---------------------------------------------------	-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------



FMBXXX

[Expand]

[FMB001](#)

[FMB010](#)

[FMB100](#)

[FMB110](#)

[FMB120](#)

[FMB122](#)

[FMB125](#)

[FMB130](#)

[FMB900](#)

[FMB920](#)

[FMB962](#)

[FMB964](#)

[FM3001](#)

[FM3010](#)

[FMB202](#)

[FMB204](#)

[FMB206](#)

[FMB207](#)

[FMB208](#)

[FMB209](#)

[FMT100](#)

[MTB100](#)

[TMT250](#)

[GH5200](#)

[FMB140](#)

[FMB020](#)

[FMB002](#)

[FMB003](#)

[FMU120](#)

[FMU122](#)

[FMU125](#)

[FMU126](#)

[FMU130](#)

[FMC120](#)

[FMC122](#)

[FMC125](#)

[FMC130](#)

[FMM12](#)

[5](#)

[FMM13](#)

[0](#)

[FMC001](#)

[FMM00](#)

[1](#)

[TFT100](#)

[FMB910](#)

[FMP100](#)

[FMP1M](#)

[1](#)

[MSP500](#)

[EMC800](#)

[FMM80](#)

[0](#)

[FMC880](#)

[FMM88](#)

[0](#)

[FMM80](#)

[A](#)

Permanent I/O elements

452

BLE RFID #2

8

HEX

0

0xffffffff  
ffffffff

-

-

BLE NBL-T RFID ID for Connentionless mode #2 slot

453	BLE RFID #3	8	HEX	0	0xffffffff ffffffff	-	-	BLE NBL-T RFID ID for Connentionless mode #3 slot	<a href="#">FMBXXX</a> <a href="#">[Expand]</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB100</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FM3010</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB207</a> <a href="#">FMB208</a> <a href="#">FMB209</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">TMT250</a> <a href="#">GH5200</a> <a href="#">FMB140</a> <a href="#">FMB020</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMU120</a> <a href="#">FMU122</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC120</a> <a href="#">FMC122</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM12</a> 5 <a href="#">FMM13</a> 0 <a href="#">FMC001</a> <a href="#">FMM00</a> 1 <a href="#">TFT100</a> <a href="#">FMB910</a> <a href="#">FMP100</a> <a href="#">FMP1M</a> 1 <a href="#">MSP500</a> <a href="#">EMC800</a> <a href="#">FMM80</a> 0 <a href="#">FMC880</a> <a href="#">FMM88</a> 0 <a href="#">FMM80</a> A	Permanent I/O elements
-----	-------------	---	-----	---	------------------------	---	---	---------------------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	------------------------



										<a href="#">FMBXXX</a>	
										<a href="#">[Expand]</a>	
										<a href="#">FMB001</a>	
										<a href="#">FMB010</a>	
										<a href="#">FMB100</a>	
										<a href="#">FMB110</a>	
										<a href="#">FMB120</a>	
										<a href="#">FMB122</a>	
										<a href="#">FMB125</a>	
										<a href="#">FMB130</a>	
										<a href="#">FMB900</a>	
										<a href="#">FMB920</a>	
										<a href="#">FMB962</a>	
										<a href="#">FMB964</a>	
										<a href="#">FM3001</a>	
										<a href="#">FM3010</a>	
										<a href="#">FMB202</a>	
										<a href="#">FMB204</a>	
										<a href="#">FMB206</a>	
										<a href="#">FMB207</a>	
										<a href="#">FMB208</a>	
										<a href="#">FMB209</a>	
										<a href="#">FMT100</a>	
										<a href="#">MTB100</a>	
										<a href="#">TMT250</a>	
										<a href="#">GH5200</a>	
										<a href="#">FMB140</a>	
										<a href="#">FMB020</a>	
										<a href="#">FMB002</a>	
455	BLE Button 1 state #1	1	Unsigned	0	1	-	-		BLE NBL-T Button 1 status for Connexionless mode #1 slot	<a href="#">FMB003</a>	Permanent I/O elements
										<a href="#">FMU120</a>	
										<a href="#">FMU122</a>	
										<a href="#">FMU125</a>	
										<a href="#">FMU126</a>	
										<a href="#">FMU130</a>	
										<a href="#">FMC120</a>	
										<a href="#">FMC122</a>	
										<a href="#">FMC125</a>	
										<a href="#">FMC130</a>	
										<a href="#">FMM125</a>	
										<a href="#">FMM130</a>	
										<a href="#">FMC001</a>	
										<a href="#">FMM001</a>	
										<a href="#">TFT100</a>	
										<a href="#">FMB910</a>	
										<a href="#">FMP100</a>	
										<a href="#">FMP1M</a>	
										<a href="#">MSP500</a>	
										<a href="#">EMC800</a>	
										<a href="#">FMM800</a>	
										<a href="#">FMC880</a>	
										<a href="#">FMM880</a>	
										<a href="#">FMM80A</a>	



													<a href="#">FMBXXX</a>	
													<a href="#">[Expand]</a>	
													<a href="#">FMB001</a>	
													<a href="#">FMB010</a>	
													<a href="#">FMB100</a>	
													<a href="#">FMB110</a>	
													<a href="#">FMB120</a>	
													<a href="#">FMB122</a>	
													<a href="#">FMB125</a>	
													<a href="#">FMB130</a>	
													<a href="#">FMB900</a>	
													<a href="#">FMB920</a>	
													<a href="#">FMB962</a>	
													<a href="#">FMB964</a>	
													<a href="#">FM3001</a>	
													<a href="#">FM3010</a>	
													<a href="#">FMB202</a>	
													<a href="#">FMB204</a>	
													<a href="#">FMB206</a>	
													<a href="#">FMB207</a>	
													<a href="#">FMB208</a>	
													<a href="#">FMB209</a>	
													<a href="#">FMT100</a>	
													<a href="#">MTB100</a>	
													<a href="#">TMT250</a>	
													<a href="#">GH5200</a>	
													<a href="#">FMB140</a>	
													<a href="#">FMB020</a>	
													<a href="#">FMB002</a>	
457	BLE Button 1 state #3	1	Unsigned	0	1	-	-						<a href="#">FMB003</a>	Permanent I/O elements
			ed										<a href="#">FMU120</a>	
													<a href="#">FMU122</a>	
													<a href="#">FMU125</a>	
													<a href="#">FMU126</a>	
													<a href="#">FMU130</a>	
													<a href="#">FMC120</a>	
													<a href="#">FMC122</a>	
													<a href="#">FMC125</a>	
													<a href="#">FMC130</a>	
													<a href="#">FMM125</a>	
													<a href="#">FMM130</a>	
													<a href="#">FMC001</a>	
													<a href="#">FMM001</a>	
													<a href="#">FMM000</a>	
													<a href="#">TFT100</a>	
													<a href="#">FMB910</a>	
													<a href="#">FMP100</a>	
													<a href="#">FMP1M</a>	
													<a href="#">MSP500</a>	
													<a href="#">EMC800</a>	
													<a href="#">FMM800</a>	
													<a href="#">FMC880</a>	
													<a href="#">FMM880</a>	
													<a href="#">FMM80A</a>	

									<a href="#">FMBXXX</a>	
									<a href="#">[Expand]</a>	
									<a href="#">FMB001</a>	
									<a href="#">FMB010</a>	
									<a href="#">FMB100</a>	
									<a href="#">FMB110</a>	
									<a href="#">FMB120</a>	
									<a href="#">FMB122</a>	
									<a href="#">FMB125</a>	
									<a href="#">FMB130</a>	
									<a href="#">FMB900</a>	
									<a href="#">FMB920</a>	
									<a href="#">FMB962</a>	
									<a href="#">FMB964</a>	
									<a href="#">FM3001</a>	
									<a href="#">FM3010</a>	
									<a href="#">FMB202</a>	
									<a href="#">FMB204</a>	
									<a href="#">FMB206</a>	
									<a href="#">FMB207</a>	
									<a href="#">FMB208</a>	
									<a href="#">FMB209</a>	
									<a href="#">FMT100</a>	
									<a href="#">MTB100</a>	
									<a href="#">TMT250</a>	
									<a href="#">GH5200</a>	
									<a href="#">FMB140</a>	
									<a href="#">FMB020</a>	
									<a href="#">FMB002</a>	
458	BLE Button 1 state #4	1	Unsigned	0	1	-	-	BLE NBL-T Button 1 status for Connexionless mode #4 slot	<a href="#">FMB003</a>	Permanent I/O elements
									<a href="#">FMU120</a>	
									<a href="#">FMU122</a>	
									<a href="#">FMU125</a>	
									<a href="#">FMU126</a>	
									<a href="#">FMU130</a>	
									<a href="#">FMC120</a>	
									<a href="#">FMC122</a>	
									<a href="#">FMC125</a>	
									<a href="#">FMC130</a>	
									<a href="#">FMM125</a>	
									<a href="#">FMM130</a>	
									<a href="#">FMC001</a>	
									<a href="#">FMM001</a>	
									<a href="#">TFT100</a>	
									<a href="#">FMB910</a>	
									<a href="#">FMP100</a>	
									<a href="#">FMP1M</a>	
									<a href="#">MSP500</a>	
									<a href="#">EMC800</a>	
									<a href="#">FMM800</a>	
									<a href="#">FMC880</a>	
									<a href="#">FMM880</a>	
									<a href="#">FMM80A</a>	

[FMBXXX](#)  
[\[Expand\]](#)  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMB208](#)  
[FMB209](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
[5](#)  
[FMM13](#)  
[0](#)  
[FMC001](#)  
[FMM00](#)  
[1](#)  
[TFT100](#)  
[FMB910](#)  
[FMP100](#)  
[FMP1M](#)  
[1](#)  
[MSP500](#)  
[EMC800](#)  
[FMM80](#)  
[0](#)  
[FMC880](#)  
[FMM88](#)  
[0](#)  
[FMM80](#)  
[A](#)

459 BLE Button 2 state #1 1 Unsigned 0 1 - - BLE NBL-T Button 2 status for Connexionless mode #1 slot

Permanent I/O elements



460	BLE Button 2 state #2	1	Unsigned	0	1	-	-	BLE NBL-T Button 2 status for Connentionless mode #2 slot	<a href="#">FMBXXX</a> <a href="#">[Expand]</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB100</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FM3010</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB207</a> <a href="#">FMB208</a> <a href="#">FMB209</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">TMT250</a> <a href="#">GH5200</a> <a href="#">FMB140</a> <a href="#">FMB020</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMU120</a> <a href="#">FMU122</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC120</a> <a href="#">FMC122</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM125</a> <a href="#">FMM130</a> <a href="#">FMC001</a> <a href="#">FMM001</a> <a href="#">TFT100</a> <a href="#">FMB910</a> <a href="#">FMP100</a> <a href="#">FMP1M1</a> <a href="#">MSP500</a> <a href="#">EMC800</a> <a href="#">FMM800</a> <a href="#">FMC880</a> <a href="#">FMM880</a> <a href="#">FMM80A</a>	Permanent I/O elements
-----	-----------------------	---	----------	---	---	---	---	-----------------------------------------------------------	----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	------------------------

[FMBXXX](#)  
[\[Expand\]](#)  
[FMB001](#)  
[FMB010](#)  
[FMB100](#)  
[FMB110](#)  
[FMB120](#)  
[FMB122](#)  
[FMB125](#)  
[FMB130](#)  
[FMB900](#)  
[FMB920](#)  
[FMB962](#)  
[FMB964](#)  
[FM3001](#)  
[FM3010](#)  
[FMB202](#)  
[FMB204](#)  
[FMB206](#)  
[FMB207](#)  
[FMB208](#)  
[FMB209](#)  
[FMT100](#)  
[MTB100](#)  
[TMT250](#)  
[GH5200](#)  
[FMB140](#)  
[FMB020](#)  
[FMB002](#)  
[FMB003](#)  
[FMU120](#)  
[FMU122](#)  
[FMU125](#)  
[FMU126](#)  
[FMU130](#)  
[FMC120](#)  
[FMC122](#)  
[FMC125](#)  
[FMC130](#)  
[FMM12](#)  
[5](#)  
[FMM13](#)  
[0](#)  
[FMC001](#)  
[FMM00](#)  
[1](#)  
[TFT100](#)  
[FMB910](#)  
[FMP100](#)  
[FMP1M](#)  
[1](#)  
[MSP500](#)  
[EMC800](#)  
[FMM80](#)  
[0](#)  
[FMC880](#)  
[FMM88](#)  
[0](#)  
[FMM80](#)  
[A](#)

461 BLE Button 2 state #3 1 Unsigned 0 1 - - BLE NBL-T Button 2 status for Connentionless mode #3 slot

Permanent I/O elements

									<a href="#">FMBXXX</a>	
									<a href="#">[Expand]</a>	
									<a href="#">FMB001</a>	
									<a href="#">FMB010</a>	
									<a href="#">FMB100</a>	
									<a href="#">FMB110</a>	
									<a href="#">FMB120</a>	
									<a href="#">FMB122</a>	
									<a href="#">FMB125</a>	
									<a href="#">FMB130</a>	
									<a href="#">FMB900</a>	
									<a href="#">FMB920</a>	
									<a href="#">FMB962</a>	
									<a href="#">FMB964</a>	
									<a href="#">FM3001</a>	
									<a href="#">FM3010</a>	
									<a href="#">FMB202</a>	
									<a href="#">FMB204</a>	
									<a href="#">FMB206</a>	
									<a href="#">FMB207</a>	
									<a href="#">FMB208</a>	
									<a href="#">FMB209</a>	
									<a href="#">FMT100</a>	
									<a href="#">MTB100</a>	
									<a href="#">TMT250</a>	
									<a href="#">GH5200</a>	
									<a href="#">FMB140</a>	
									<a href="#">FMB020</a>	
									<a href="#">FMB002</a>	
462	BLE Button 2 state #4	1	Unsigned	0	1	-	-	BLE NBL-T Button 2 status for Connentionless mode #4 slot	<a href="#">FMB003</a>	Permanent I/O elements
			ed						<a href="#">FMU120</a>	
									<a href="#">FMU122</a>	
									<a href="#">FMU125</a>	
									<a href="#">FMU126</a>	
									<a href="#">FMU130</a>	
									<a href="#">FMC120</a>	
									<a href="#">FMC122</a>	
									<a href="#">FMC125</a>	
									<a href="#">FMC130</a>	
									<a href="#">FMM12</a>	
									<a href="#">5</a>	
									<a href="#">FMM13</a>	
									<a href="#">0</a>	
									<a href="#">FMC001</a>	
									<a href="#">FMM00</a>	
									<a href="#">1</a>	
									<a href="#">TFT100</a>	
									<a href="#">FMB910</a>	
									<a href="#">FMP100</a>	
									<a href="#">FMP1M</a>	
									<a href="#">1</a>	
									<a href="#">MSP500</a>	
									<a href="#">EMC800</a>	
									<a href="#">FMM80</a>	
									<a href="#">0</a>	
									<a href="#">FMC880</a>	
									<a href="#">FMM88</a>	
									<a href="#">0</a>	
									<a href="#">FMM80</a>	
									<a href="#">A</a>	

Address	Width	Bit	Sign	Min	Max	Unit	Description	Element
622	Frequency DIN1	2	Unsigned	0	65535	0.1 Hz	Frequency of input signal present on DIN1	Permanent I/O elements
<a href="#">FMBXXX</a> <a href="#">[Expand]</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB100</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FM3010</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB207</a> <a href="#">FMB208</a> <a href="#">FMB209</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">TMT250</a> <a href="#">GH5200</a> <a href="#">FMB140</a> <a href="#">FMB020</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMU120</a> <a href="#">FMU122</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC120</a> <a href="#">FMC122</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMC001</a> <a href="#">FMM00</a> <a href="#">1</a> <a href="#">TFT100</a> <a href="#">FMB910</a> <a href="#">FMP100</a> <a href="#">FMP1M</a> <a href="#">1</a> <a href="#">MSP500</a> <a href="#">FMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMC880</a> <a href="#">FMM88</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>								

623	Frequency DIN2	2	Unsigned	0	65535	0.1	Hz	Frequency of input signal present on DIN2	<a href="#">FMBXXX</a> <a href="#">[Expand]</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB100</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FM3010</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB207</a> <a href="#">FMB208</a> <a href="#">FMB209</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">TMT250</a> <a href="#">GH5200</a> <a href="#">FMB140</a> <a href="#">FMB020</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMU120</a> <a href="#">FMU122</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC120</a> <a href="#">FMC122</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMC001</a> <a href="#">FMM00</a> <a href="#">1</a> <a href="#">TFT100</a> <a href="#">FMB910</a> <a href="#">FMP100</a> <a href="#">FMP1M</a> <a href="#">1</a> <a href="#">MSP500</a> <a href="#">EMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMC880</a> <a href="#">FMM88</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	Permanent I/O elements
-----	----------------	---	----------	---	-------	-----	----	-------------------------------------------	------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	------------------------

## Eventual I/O elements

Property ID in AVE packet	Property Name	Bytes	Type	Value range	Multiplier	Units	Description	HW Support	Parameter Group
155	Guidance zone 01	1	Unsigned	0 - 3	-	-	0 - target left zone 1 - target entered zone 2 - cover opening end 3 - cover opening start	<a href="#">FMBXXX</a> <a href="#">FMB001</a> <a href="#">FMB010</a> <a href="#">FMB100</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMB130</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FM3001</a> <a href="#">FM3010</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMB207</a> <a href="#">FMB208</a> <a href="#">FMB209</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">TMT250</a> <a href="#">GH5200</a> <a href="#">FMB140</a> <a href="#">FMB020</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMU120</a> <a href="#">FMU122</a> <a href="#">FMU125</a> <a href="#">FMU126</a> <a href="#">FMU130</a> <a href="#">FMC120</a> <a href="#">FMC122</a> <a href="#">FMC125</a> <a href="#">FMC130</a> <a href="#">FMM12</a> <a href="#">5</a> <a href="#">FMM13</a> <a href="#">0</a> <a href="#">FMC001</a> <a href="#">FMM00</a> <a href="#">1</a> <a href="#">TFT100</a> <a href="#">FMB910</a> <a href="#">FMP100</a> <a href="#">FMP1M</a> <a href="#">1</a> <a href="#">MSP500</a> <a href="#">EMC800</a> <a href="#">FMM80</a> <a href="#">0</a> <a href="#">FMC880</a> <a href="#">FMM88</a> <a href="#">0</a> <a href="#">FMM80</a> <a href="#">A</a>	Eventual I/O elements











219	Confidence zone 38	1	Unassigned	0	3	-	-	0 - target left zone 1 - target entered zone 2 - over spending end 3 - over spending start	FM5XXX 2410001	Eventual IO elements
									2410002	
									2410003	
									2410004	
									2410005	
									2410006	
									2410007	
									2410008	
									2410009	
									2410010	
									2410011	
									2410012	
220	Confidence zone 39	1	Unassigned	0	3	-	-	0 - target left zone 1 - target entered zone 2 - over spending end 3 - over spending start	FM5XXX 2410013	Eventual IO elements
									2410014	
									2410015	
									2410016	
									2410017	
									2410018	
									2410019	
									2410020	
									2410021	
									2410022	
									2410023	
									2410024	
221	Confidence zone 40	1	Unassigned	0	3	-	-	0 - target left zone 1 - target entered zone 2 - over spending end 3 - over spending start	FM5XXX 2410025	Eventual IO elements
									2410026	
									2410027	
									2410028	
									2410029	
									2410030	
									2410031	
									2410032	
									2410033	
									2410034	
									2410035	
									2410036	
222	Confidence zone 41	1	Unassigned	0	3	-	-	0 - target left zone 1 - target entered zone 2 - over spending end 3 - over spending start	FM5XXX 2410037	Eventual IO elements
									2410038	
									2410039	
									2410040	
									2410041	
									2410042	
									2410043	
									2410044	
									2410045	
									2410046	
									2410047	
									2410048	
223	Confidence zone 42	1	Unassigned	0	3	-	-	0 - target left zone 1 - target entered zone 2 - over spending end 3 - over spending start	FM5XXX 2410049	Eventual IO elements
									2410050	
									2410051	
									2410052	
									2410053	
									2410054	
									2410055	
									2410056	
									2410057	
									2410058	
									2410059	
									2410060	
224	Confidence zone 43	1	Unassigned	0	3	-	-	0 - target left zone 1 - target entered zone 2 - over spending end 3 - over spending start	FM5XXX 2410061	Eventual IO elements
									2410062	
									2410063	
									2410064	
									2410065	
									2410066	
									2410067	
									2410068	
									2410069	
									2410070	
									2410071	
									2410072	
225	Confidence zone 44	1	Unassigned	0	3	-	-	0 - target left zone 1 - target entered zone 2 - over spending end 3 - over spending start	FM5XXX 2410073	Eventual IO elements
									2410074	
									2410075	
									2410076	
									2410077	
									2410078	
									2410079	
									2410080	
									2410081	
									2410082	
									2410083	
									2410084	
226	Confidence zone 45	1	Unassigned	0	3	-	-	0 - target left zone 1 - target entered zone 2 - over spending end 3 - over spending start	FM5XXX 2410085	Eventual IO elements
									2410086	
									2410087	
									2410088	
									2410089	
									2410090	
									2410091	
									2410092	
									2410093	
									2410094	
									2410095	
									2410096	
227	Confidence zone 46	1	Unassigned	0	3	-	-	0 - target left zone 1 - target entered zone 2 - over spending end 3 - over spending start	FM5XXX 2410097	Eventual IO elements
									2410098	
									2410099	
									2411000	
									2411001	
									2411002	
									2411003	
									2411004	
									2411005	
									2411006	
									2411007	
									2411008	



Event ID	Event Name	Severity	Category	Priority	Frequency	Impact	Resolution	Source	Event ID elements
253	Green driving type	1	Unassigned	1	3	-	-	1 - harsh acceleration 2 - harsh braking 3 - harsh cornering	Eventual EO elements
246	Towing	1	Unassigned	0	1	-	-	0 - steady 1 - towing	Eventual EO elements
252	Unlupig	1	Unassigned	0	1	-	-	0 - battery present 1 - battery employed	Eventual EO elements
247	Crash detection	1	Unassigned	1	6	-	-	1 - real crash detected (device is calibrated) 2 - limited crash trace (device not calibrated) 3 - limited crash trace (device is calibrated) 4 - full crash trace (device not calibrated) 5 - full crash trace (device is calibrated) 6 - real crash detected (device not calibrated)	Eventual EO elements
248	Immobilizer	1	Unassigned	0	2	-	-	0 - Illicion not connected 1 - Illicion connected (Unauthorized) 2 - Illicion connected (Authorized Driving)	Eventual EO elements
254	Green Driving Value	1	Unassigned	0	255	sec and braking 0.01	G or red	Dependent on green driving type: if harsh acceleration or braking - g*100 (value 123 => 1.23g). If Green driving source is „GPS“ - harsh cornering value in rad*100. If source is „Accelerometer“ - g*100.	Eventual EO elements
249	Jamming	1	Unassigned	0	1	-	-	0 - jamming stop 1 - jamming start	Eventual EO elements
14	ECDCID	8	Unassigned	0	0xFFFFFFFFFFFFFFFF	-	-	Value of SID ECDC_LSB	Eventual EO elements
243	Green driving event duration	2	Unassigned	0	65535	-	ms	Duration of event that did generate Green driving	Eventual EO elements
236	Alert	1	Unassigned	0	1	-	-	0 - Reserved 1 - Alarm event occurred	Eventual EO elements
258	EcoMaximum	8	Unassigned	0	0xFFFFFFFFFFFFFFFF	-	-	Eventual alarm maximum accelerometer values in mg on all axis during Eco driving event 8 Bytes 28 X-axis 28 - Y-axis 28 - Z-axis	Eventual EO elements
259	EcoAverage	8	Unassigned	0	0xFFFFFFFFFFFFFFFF	-	-	Eventual alarm average accelerometer values in mg on all axis during Eco driving event 8 Bytes 28 X-axis 28 - Y-axis 28 - Z-axis	Eventual EO elements
260	EcoDuration	2	Unassigned	0	65535	-	ms	Duration of Eco driving event in milliseconds	Eventual EO elements

283	Driving State	1	Unsigned	0	3	-	-	1 - Ignition ON 2 - Driving on 3 - Ignition OFF	<a href="#">DM110</a>	Eventual IO elements
284	Driving Records	2	Unsigned	0	65535	-	-	Number of Records between Ignition ON and Ignition OFF	<a href="#">DM110</a> FMBXXX 040001 <a href="#">FMB001</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMB004</a> <a href="#">FMB005</a> <a href="#">FMB006</a> <a href="#">FMB007</a> <a href="#">FMB008</a> <a href="#">FMB009</a> <a href="#">FMB010</a> <a href="#">FMB011</a> <a href="#">FMB012</a> <a href="#">FMB013</a> <a href="#">FMB014</a> <a href="#">FMB015</a> <a href="#">FMB016</a> <a href="#">FMB017</a> <a href="#">FMB018</a> <a href="#">FMB019</a> <a href="#">FMB020</a> <a href="#">FMB021</a> <a href="#">FMB022</a> <a href="#">FMB023</a> <a href="#">FMB024</a> <a href="#">FMB025</a> <a href="#">FMB026</a> <a href="#">FMB027</a> <a href="#">FMB028</a> <a href="#">FMB029</a> <a href="#">FMB030</a> <a href="#">FMB031</a> <a href="#">FMB032</a> <a href="#">FMB033</a> <a href="#">FMB034</a> <a href="#">FMB035</a> <a href="#">FMB036</a> <a href="#">FMB037</a> <a href="#">FMB038</a> <a href="#">FMB039</a> <a href="#">FMB040</a> <a href="#">FMB041</a> <a href="#">FMB042</a> <a href="#">FMB043</a> <a href="#">FMB044</a> <a href="#">FMB045</a> <a href="#">FMB046</a> <a href="#">FMB047</a> <a href="#">FMB048</a> <a href="#">FMB049</a> <a href="#">FMB050</a> <a href="#">FMB051</a> <a href="#">FMB052</a> <a href="#">FMB053</a> <a href="#">FMB054</a> <a href="#">FMB055</a> <a href="#">FMB056</a> <a href="#">FMB057</a> <a href="#">FMB058</a> <a href="#">FMB059</a> <a href="#">FMB060</a> <a href="#">FMB061</a> <a href="#">FMB062</a> <a href="#">FMB063</a> <a href="#">FMB064</a> <a href="#">FMB065</a> <a href="#">FMB066</a> <a href="#">FMB067</a> <a href="#">FMB068</a> <a href="#">FMB069</a> <a href="#">FMB070</a> <a href="#">FMB071</a> <a href="#">FMB072</a> <a href="#">FMB073</a> <a href="#">FMB074</a> <a href="#">FMB075</a> <a href="#">FMB076</a> <a href="#">FMB077</a> <a href="#">FMB078</a> <a href="#">FMB079</a> <a href="#">FMB080</a> <a href="#">FMB081</a> <a href="#">FMB082</a> <a href="#">FMB083</a> <a href="#">FMB084</a> <a href="#">FMB085</a> <a href="#">FMB086</a> <a href="#">FMB087</a> <a href="#">FMB088</a> <a href="#">FMB089</a> <a href="#">FMB090</a> <a href="#">FMB091</a> <a href="#">FMB092</a> <a href="#">FMB093</a> <a href="#">FMB094</a> <a href="#">FMB095</a> <a href="#">FMB096</a> <a href="#">FMB097</a> <a href="#">FMB098</a> <a href="#">FMB099</a> <a href="#">FMB100</a>	Eventual IO elements
317	Crash event counter	1	Unsigned	0	255	-	-	Contacts trace with specific eventual crash record	<a href="#">FMB001</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMB004</a> <a href="#">FMB005</a> <a href="#">FMB006</a> <a href="#">FMB007</a> <a href="#">FMB008</a> <a href="#">FMB009</a> <a href="#">FMB010</a> <a href="#">FMB011</a> <a href="#">FMB012</a> <a href="#">FMB013</a> <a href="#">FMB014</a> <a href="#">FMB015</a> <a href="#">FMB016</a> <a href="#">FMB017</a> <a href="#">FMB018</a> <a href="#">FMB019</a> <a href="#">FMB020</a> <a href="#">FMB021</a> <a href="#">FMB022</a> <a href="#">FMB023</a> <a href="#">FMB024</a> <a href="#">FMB025</a> <a href="#">FMB026</a> <a href="#">FMB027</a> <a href="#">FMB028</a> <a href="#">FMB029</a> <a href="#">FMB030</a> <a href="#">FMB031</a> <a href="#">FMB032</a> <a href="#">FMB033</a> <a href="#">FMB034</a> <a href="#">FMB035</a> <a href="#">FMB036</a> <a href="#">FMB037</a> <a href="#">FMB038</a> <a href="#">FMB039</a> <a href="#">FMB040</a> <a href="#">FMB041</a> <a href="#">FMB042</a> <a href="#">FMB043</a> <a href="#">FMB044</a> <a href="#">FMB045</a> <a href="#">FMB046</a> <a href="#">FMB047</a> <a href="#">FMB048</a> <a href="#">FMB049</a> <a href="#">FMB050</a> <a href="#">FMB051</a> <a href="#">FMB052</a> <a href="#">FMB053</a> <a href="#">FMB054</a> <a href="#">FMB055</a> <a href="#">FMB056</a> <a href="#">FMB057</a> <a href="#">FMB058</a> <a href="#">FMB059</a> <a href="#">FMB060</a> <a href="#">FMB061</a> <a href="#">FMB062</a> <a href="#">FMB063</a> <a href="#">FMB064</a> <a href="#">FMB065</a> <a href="#">FMB066</a> <a href="#">FMB067</a> <a href="#">FMB068</a> <a href="#">FMB069</a> <a href="#">FMB070</a> <a href="#">FMB071</a> <a href="#">FMB072</a> <a href="#">FMB073</a> <a href="#">FMB074</a> <a href="#">FMB075</a> <a href="#">FMB076</a> <a href="#">FMB077</a> <a href="#">FMB078</a> <a href="#">FMB079</a> <a href="#">FMB080</a> <a href="#">FMB081</a> <a href="#">FMB082</a> <a href="#">FMB083</a> <a href="#">FMB084</a> <a href="#">FMB085</a> <a href="#">FMB086</a> <a href="#">FMB087</a> <a href="#">FMB088</a> <a href="#">FMB089</a> <a href="#">FMB090</a> <a href="#">FMB091</a> <a href="#">FMB092</a> <a href="#">FMB093</a> <a href="#">FMB094</a> <a href="#">FMB095</a> <a href="#">FMB096</a> <a href="#">FMB097</a> <a href="#">FMB098</a> <a href="#">FMB099</a> <a href="#">FMB100</a>	Eventual IO elements
318	GNSS Jamming	1	Unsigned	0	2	-	-	GNSS Jamming state: 0 - GPS jamming not detected/healthy state 1 - GPS jamming warning state 2 - GPS jamming critical state	<a href="#">FMB001</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMB004</a> <a href="#">FMB005</a> <a href="#">FMB006</a> <a href="#">FMB007</a> <a href="#">FMB008</a> <a href="#">FMB009</a> <a href="#">FMB010</a> <a href="#">FMB011</a> <a href="#">FMB012</a> <a href="#">FMB013</a> <a href="#">FMB014</a> <a href="#">FMB015</a> <a href="#">FMB016</a> <a href="#">FMB017</a> <a href="#">FMB018</a> <a href="#">FMB019</a> <a href="#">FMB020</a> <a href="#">FMB021</a> <a href="#">FMB022</a> <a href="#">FMB023</a> <a href="#">FMB024</a> <a href="#">FMB025</a> <a href="#">FMB026</a> <a href="#">FMB027</a> <a href="#">FMB028</a> <a href="#">FMB029</a> <a href="#">FMB030</a> <a href="#">FMB031</a> <a href="#">FMB032</a> <a href="#">FMB033</a> <a href="#">FMB034</a> <a href="#">FMB035</a> <a href="#">FMB036</a> <a href="#">FMB037</a> <a href="#">FMB038</a> <a href="#">FMB039</a> <a href="#">FMB040</a> <a href="#">FMB041</a> <a href="#">FMB042</a> <a href="#">FMB043</a> <a href="#">FMB044</a> <a href="#">FMB045</a> <a href="#">FMB046</a> <a href="#">FMB047</a> <a href="#">FMB048</a> <a href="#">FMB049</a> <a href="#">FMB050</a> <a href="#">FMB051</a> <a href="#">FMB052</a> <a href="#">FMB053</a> <a href="#">FMB054</a> <a href="#">FMB055</a> <a href="#">FMB056</a> <a href="#">FMB057</a> <a href="#">FMB058</a> <a href="#">FMB059</a> <a href="#">FMB060</a> <a href="#">FMB061</a> <a href="#">FMB062</a> <a href="#">FMB063</a> <a href="#">FMB064</a> <a href="#">FMB065</a> <a href="#">FMB066</a> <a href="#">FMB067</a> <a href="#">FMB068</a> <a href="#">FMB069</a> <a href="#">FMB070</a> <a href="#">FMB071</a> <a href="#">FMB072</a> <a href="#">FMB073</a> <a href="#">FMB074</a> <a href="#">FMB075</a> <a href="#">FMB076</a> <a href="#">FMB077</a> <a href="#">FMB078</a> <a href="#">FMB079</a> <a href="#">FMB080</a> <a href="#">FMB081</a> <a href="#">FMB082</a> <a href="#">FMB083</a> <a href="#">FMB084</a> <a href="#">FMB085</a> <a href="#">FMB086</a> <a href="#">FMB087</a> <a href="#">FMB088</a> <a href="#">FMB089</a> <a href="#">FMB090</a> <a href="#">FMB091</a> <a href="#">FMB092</a> <a href="#">FMB093</a> <a href="#">FMB094</a> <a href="#">FMB095</a> <a href="#">FMB096</a> <a href="#">FMB097</a> <a href="#">FMB098</a> <a href="#">FMB099</a> <a href="#">FMB100</a>	Eventual IO elements
391	Private mode	1	Unsigned	0	255	-	-	Private mode state: 0 - Private mode off 1 - Private mode on	<a href="#">FMB001</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMB004</a> <a href="#">FMB005</a> <a href="#">FMB006</a> <a href="#">FMB007</a> <a href="#">FMB008</a> <a href="#">FMB009</a> <a href="#">FMB010</a> <a href="#">FMB011</a> <a href="#">FMB012</a> <a href="#">FMB013</a> <a href="#">FMB014</a> <a href="#">FMB015</a> <a href="#">FMB016</a> <a href="#">FMB017</a> <a href="#">FMB018</a> <a href="#">FMB019</a> <a href="#">FMB020</a> <a href="#">FMB021</a> <a href="#">FMB022</a> <a href="#">FMB023</a> <a href="#">FMB024</a> <a href="#">FMB025</a> <a href="#">FMB026</a> <a href="#">FMB027</a> <a href="#">FMB028</a> <a href="#">FMB029</a> <a href="#">FMB030</a> <a href="#">FMB031</a> <a href="#">FMB032</a> <a href="#">FMB033</a> <a href="#">FMB034</a> <a href="#">FMB035</a> <a href="#">FMB036</a> <a href="#">FMB037</a> <a href="#">FMB038</a> <a href="#">FMB039</a> <a href="#">FMB040</a> <a href="#">FMB041</a> <a href="#">FMB042</a> <a href="#">FMB043</a> <a href="#">FMB044</a> <a href="#">FMB045</a> <a href="#">FMB046</a> <a href="#">FMB047</a> <a href="#">FMB048</a> <a href="#">FMB049</a> <a href="#">FMB050</a> <a href="#">FMB051</a> <a href="#">FMB052</a> <a href="#">FMB053</a> <a href="#">FMB054</a> <a href="#">FMB055</a> <a href="#">FMB056</a> <a href="#">FMB057</a> <a href="#">FMB058</a> <a href="#">FMB059</a> <a href="#">FMB060</a> <a href="#">FMB061</a> <a href="#">FMB062</a> <a href="#">FMB063</a> <a href="#">FMB064</a> <a href="#">FMB065</a> <a href="#">FMB066</a> <a href="#">FMB067</a> <a href="#">FMB068</a> <a href="#">FMB069</a> <a href="#">FMB070</a> <a href="#">FMB071</a> <a href="#">FMB072</a> <a href="#">FMB073</a> <a href="#">FMB074</a> <a href="#">FMB075</a> <a href="#">FMB076</a> <a href="#">FMB077</a> <a href="#">FMB078</a> <a href="#">FMB079</a> <a href="#">FMB080</a> <a href="#">FMB081</a> <a href="#">FMB082</a> <a href="#">FMB083</a> <a href="#">FMB084</a> <a href="#">FMB085</a> <a href="#">FMB086</a> <a href="#">FMB087</a> <a href="#">FMB088</a> <a href="#">FMB089</a> <a href="#">FMB090</a> <a href="#">FMB091</a> <a href="#">FMB092</a> <a href="#">FMB093</a> <a href="#">FMB094</a> <a href="#">FMB095</a> <a href="#">FMB096</a> <a href="#">FMB097</a> <a href="#">FMB098</a> <a href="#">FMB099</a> <a href="#">FMB100</a>	Eventual IO elements
449	Ignition On Counter	4	Unsigned	0	2147483647	-	x	Duration in seconds which is counted while Ignition state is On	<a href="#">FMB001</a> <a href="#">FMB002</a> <a href="#">FMB003</a> <a href="#">FMB004</a> <a href="#">FMB005</a> <a href="#">FMB006</a> <a href="#">FMB007</a> <a href="#">FMB008</a> <a href="#">FMB009</a> <a href="#">FMB010</a> <a href="#">FMB011</a> <a href="#">FMB012</a> <a href="#">FMB013</a> <a href="#">FMB014</a> <a href="#">FMB015</a> <a href="#">FMB016</a> <a href="#">FMB017</a> <a href="#">FMB018</a> <a href="#">FMB019</a> <a href="#">FMB020</a> <a href="#">FMB021</a> <a href="#">FMB022</a> <a href="#">FMB023</a> <a href="#">FMB024</a> <a href="#">FMB025</a> <a href="#">FMB026</a> <a href="#">FMB027</a> <a href="#">FMB028</a> <a href="#">FMB029</a> <a href="#">FMB030</a> <a href="#">FMB031</a> <a href="#">FMB032</a> <a href="#">FMB033</a> <a href="#">FMB034</a> <a href="#">FMB035</a> <a href="#">FMB036</a> <a href="#">FMB037</a> <a href="#">FMB038</a> <a href="#">FMB039</a> <a href="#">FMB040</a> <a href="#">FMB041</a> <a href="#">FMB042</a> <a href="#">FMB043</a> <a href="#">FMB044</a> <a href="#">FMB045</a> <a href="#">FMB046</a> <a href="#">FMB047</a> <a href="#">FMB048</a> <a href="#">FMB049</a> <a href="#">FMB050</a> <a href="#">FMB051</a> <a href="#">FMB052</a> <a href="#">FMB053</a> <a href="#">FMB054</a> <a href="#">FMB055</a> <a href="#">FMB056</a> <a href="#">FMB057</a> <a href="#">FMB058</a> <a href="#">FMB059</a> <a href="#">FMB060</a> <a href="#">FMB061</a> <a href="#">FMB062</a> <a href="#">FMB063</a> <a href="#">FMB064</a> <a href="#">FMB065</a> <a href="#">FMB066</a> <a href="#">FMB067</a> <a href="#">FMB068</a> <a href="#">FMB069</a> <a href="#">FMB070</a> <a href="#">FMB071</a> <a href="#">FMB072</a> <a href="#">FMB073</a> <a href="#">FMB074</a> <a href="#">FMB075</a> <a href="#">FMB076</a> <a href="#">FMB077</a> <a href="#">FMB078</a> <a href="#">FMB079</a> <a href="#">FMB080</a> <a href="#">FMB081</a> <a href="#">FMB082</a> <a href="#">FMB083</a> <a href="#">FMB084</a> <a href="#">FMB085</a> <a href="#">FMB086</a> <a href="#">FMB087</a> <a href="#">FMB088</a> <a href="#">FMB089</a> <a href="#">FMB090</a> <a href="#">FMB091</a> <a href="#">FMB092</a> <a href="#">FMB093</a> <a href="#">FMB094</a> <a href="#">FMB095</a> <a href="#">FMB096</a> <a href="#">FMB097</a> <a href="#">FMB098</a> <a href="#">FMB099</a> <a href="#">FMB100</a>	Eventual IO elements

## OBD elements

Property ID in AVL packet	Property Name	Bytes	Type	Value range Min Max	Multiplier	Units	Description	HW Support	Parameter Group
256	VIN	17	ASCII	0 0xff	-	-	VIN number	FMBXXX <a href="#">FMB001</a> <a href="#">FMC001</a> <a href="#">FMB010</a> <a href="#">FMB003</a> <a href="#">FMB110</a> <a href="#">FMB120</a> <a href="#">FMB122</a> <a href="#">FMB125</a> <a href="#">FMU125</a> <a href="#">FMC125</a> <a href="#">FMM125</a> <a href="#">FMB130</a> <a href="#">FMU130</a> <a href="#">FMC130</a> <a href="#">FMM130</a> <a href="#">FMB140</a> <a href="#">FMB150</a> <a href="#">FMC150</a> <a href="#">FMM150</a> <a href="#">FMB900</a> <a href="#">FMB920</a> <a href="#">FMB962</a> <a href="#">FMB964</a> <a href="#">FMS001</a> <a href="#">FMT100</a> <a href="#">MTR100</a> <a href="#">FMB202</a> <a href="#">FMB204</a> <a href="#">FMB206</a> <a href="#">FMT100</a> <a href="#">MTB100</a> <a href="#">FMB140</a>	OBD elements

									FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	
30	Number of DTC	1	Unsigned	0	255	-	-	Number of DTC	FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
31	Engine Load	1	Unsigned	0	100	-	%	Calculated engine load value	FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
32	Coolant Temperature	1	Signed	-128	127	-	°C	Engine coolant temperature	FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
33	Short Fuel Trim	1	Signed	-100	99	-	%	Short term fuel trim 1	FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements

										FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	
34	Fuel pressure	2	Unsigned	0	765	-	kPa	Fuel pressure		FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
35	Intake MAP	1	Unsigned	0	255	-	kPa	Intake manifold absolute pressure		FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
36	Engine RPM	2	Unsigned	0	16384	-	rpm	Engine RPM		FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
37	Vehicle Speed	1	Unsigned	0	255	-	km/h	Vehicle speed		FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements

38	Timing Advance	1	Signed	-64	64	-	°	Timing advance	OBD elements
39	Intake Air Temperature	1	Signed	-128	127	-	°C	Intake air temperature	OBD elements
40	MAF	2	Unsigned	0	65535	0.01	g/sec	MAF air flow rate	OBD elements
41	Throttle Position	1	Unsigned	0	100	-	%	Throttle position	OBD elements

FMBXXX  
 FMB001  
 FMC001  
 FMB010  
 FMB003  
 FMB110  
 FMB120  
 FMB122  
 FMB125  
 FMC125  
 FMC125  
 FMM125  
 FMB130  
 FMC130  
 FMC130  
 FMM130  
 FMB140  
 FMB150  
 FMC150  
 FMM150  
 FMB900  
 FMB920  
 FMB962  
 FMB964  
 FM3001  
 FMT100  
 MTB100  
 FMB202  
 FMB204  
 FMB206  
 FMT100  
 MTB100  
 FMB140  
 FMBXXX  
 FMB001  
 FMC001  
 FMB010  
 FMB003  
 FMB110  
 FMB120  
 FMB122  
 FMB125  
 FMC125  
 FMC125  
 FMM125  
 FMB130  
 FMC130  
 FMC130  
 FMM130  
 FMB140  
 FMB150  
 FMC150  
 FMM150  
 FMB900  
 FMB920  
 FMB962  
 FMB964  
 FM3001  
 FMT100  
 MTB100  
 FMB202  
 FMB204  
 FMB206  
 FMT100  
 MTB100  
 FMB140  
 FMBXXX  
 FMB001  
 FMC001  
 FMB010  
 FMB003  
 FMB110  
 FMB120  
 FMB122  
 FMB125  
 FMC125  
 FMC125  
 FMM125  
 FMB130  
 FMC130  
 FMC130  
 FMM130  
 FMB140  
 FMB150  
 FMC150  
 FMM150  
 FMB900  
 FMB920  
 FMB962  
 FMB964  
 FM3001  
 FMT100  
 MTB100  
 FMB202  
 FMB204  
 FMB206  
 FMT100  
 MTB100  
 FMB140  
 FMBXXX  
 FMB001  
 FMC001  
 FMB010  
 FMB003  
 FMB110  
 FMB120  
 FMB122  
 FMB125  
 FMC125  
 FMC125  
 FMM125  
 FMB130  
 FMC130  
 FMC130  
 FMM130  
 FMB140  
 FMB150  
 FMC150  
 FMM150  
 FMB900  
 FMB920  
 FMB962  
 FMB964  
 FM3001  
 FMT100  
 MTB100  
 FMB202  
 FMB204  
 FMB206  
 FMT100  
 MTB100  
 FMB140



										FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140 FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140 FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140 FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
42	Runtime since engine start	2	Unsigned	0	65535	-	s	Runtime since engine start			
43	Distance Traveled MIL On	2	Unsigned	0	65535	-	km	Distance ormatin MIL on			
44	Relative Fuel Rail Pressure	2	Unsigned	0	5178	0.1	kPa	Relative fuel rail pressure			
45	Direct Fuel Rail Pressure	2	Unsigned	0	65535	10	kPa	Direct Fuel Rail Pressure			

46	Commanded EGR	1	Unsigned	0	100	-	%	Commanded EGR	FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140 FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140 FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
47	EGR Error	1	Signed	-100	100	-	%	EGR error	FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140 FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140 FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
48	Fuel Level	1	Unsigned	0	100	-	%	Fuel level	FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140 FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140 FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
49	Distance Since Codes Clear	2	Unsigned	0	65535	-	km	Distance traveled since codes cleared	FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140 FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements

50	Barometric Pressure	1	Unsigned	0	255	-	kPa	Barometric pressure	FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140 FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140 FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
51	Control Module Voltage	2	Unsigned	0	65535	0.001	V	Control module voltage	FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140 FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140 FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
52	Absolute Load Value	2	Unsigned	0	25700	-	%	Absolute load value	FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140 FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
759	Fuel Type	1	Unsigned	0	255	-	-	0 Not available 1 Gasoline 2 Methanol 3 Ethanol 4 Diesel 5 LPG 6 CNG 7 Propane 8 Electric 9 Bifuel running Gasoline 10 Bifuel running Methanol 11 Bifuel running Ethanol 12 Bifuel running LPG 13 Bifuel running CNG 14 Bifuel running Propane 15 Bifuel running Electricity 16 Bifuel running electric and combustion engine 17 Hybrid gasoline 18 Hybrid Ethanol 19 Hybrid Diesel 20 Hybrid Electric 21 Hybrid running electric and combustion engine 22 Hybrid Regenerative 23 Bifuel running diesel	FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140 FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMU125 FMC125 FMM125 FMB130 FMC130 FMB130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements

										<ul style="list-style-type: none"> <li>FMBXXX</li> <li>FMB001</li> <li>FMC001</li> <li>EMB010</li> <li>EMB003</li> <li>EMB110</li> <li>EMB120</li> <li>EMB122</li> <li>EMB125</li> <li>FMU125</li> <li>FMC125</li> <li>FMM125</li> <li>FMB130</li> <li>FMU130</li> <li>FMC130</li> <li>FMM130</li> <li>EMB140</li> <li>EMB150</li> <li>FMC150</li> <li>FMM150</li> <li>EMB900</li> <li>EMB920</li> <li>EMB962</li> <li>EMB964</li> <li>FM3001</li> <li>FMT100</li> <li>MTB100</li> <li>EMB202</li> <li>EMB204</li> <li>EMB206</li> <li>FMT100</li> <li>MTB100</li> <li>FMB140</li> <li>FMBXXX</li> <li>FMB001</li> <li>FMC001</li> <li>EMB010</li> <li>EMB003</li> <li>EMB110</li> <li>EMB120</li> <li>EMB122</li> <li>EMB125</li> <li>FMU125</li> <li>FMC125</li> <li>FMM125</li> <li>FMB130</li> <li>FMU130</li> <li>FMC130</li> <li>FMM130</li> <li>EMB140</li> <li>EMB150</li> <li>FMC150</li> <li>FMM150</li> <li>EMB900</li> <li>EMB920</li> <li>EMB962</li> <li>EMB964</li> <li>FM3001</li> <li>FMT100</li> <li>MTB100</li> <li>EMB202</li> <li>EMB204</li> <li>EMB206</li> <li>FMT100</li> <li>MTB100</li> <li>FMB140</li> <li>FMBXXX</li> <li>FMB001</li> <li>FMC001</li> <li>EMB010</li> <li>EMB003</li> <li>EMB110</li> <li>EMB120</li> <li>EMB122</li> <li>EMB125</li> <li>FMU125</li> <li>FMC125</li> <li>FMM125</li> <li>FMB130</li> <li>FMU130</li> <li>FMC130</li> <li>FMM130</li> <li>EMB140</li> <li>EMB150</li> <li>FMC150</li> <li>FMM150</li> <li>EMB900</li> <li>EMB920</li> <li>EMB962</li> <li>EMB964</li> <li>FM3001</li> <li>FMT100</li> <li>MTB100</li> <li>EMB202</li> <li>EMB204</li> <li>EMB206</li> <li>FMT100</li> <li>MTB100</li> <li>FMB140</li> </ul>	OBD elements
53	Ambient Air Temperature	1	Signed	-128	127	-	°C	Ambient air temperature			
54	Time Run With MIL On	2	Unsigned	0	65535	-	min	Time run with MIL on			
55	Time Since Codes Cleared	2	Unsigned	0	65535	-	min	Time since codes cleared			
56	Absolute Fuel Rail Pressure	2	Unsigned	0	65535	0.1	kPa	Absolute fuel rail pressure			

										FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130	
57	Hybrid battery pack life	1	Unsigned	0	100	-	%	Hybrid battery pack remaining life		FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 EMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
										FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130	
58	Engine Oil Temperature	1	Unsigned	0	215	-	°C	Engine oil temperature		FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 EMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
										FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130	
59	Fuel injection timing	2	Signed	-21000	30200	0.01	°	Fuel injection timing		FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 EMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
										FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130	
540	Throttle position group	1	Unsigned	0	100	-	%	Throttle Position Value From PID Group		FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 EMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	OBD elements
										FMBXXX FMB001 FMC003 FMC00A FMM003 FMM00A	
541	Commanded Equivalence R	1	Unsigned	0	200	0.01	-	Fuel-Air Commanded Equivalence Ratio		FMBXXX FMB003 FMC003 FMC00A FMM003 FMM00A	OBD elements
										FMBXXX FMB001 FMB003 FMC003 FMC00A FMM003 FMM00A	
542	Intake MAP 2 bytes	2	Unsigned	0	2048	-	kPa	Intake Manifold Absolute Pressure		FMBXXX FMB001 FMB003 FMC003 FMC00A FMM003 FMM00A	OBD elements

										FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	
543	Hybrid System Voltage	2	Unsigned	0	1024	-	V	Hybrid vehicle system voltage		OBD elements	
										FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	
544	Hybrid System Current	2	Signed	-3277	3277	-	A	Hybrid vehicle system current		OBD elements	
										FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	
281	Fault Codes	variable	ASCII	0	128	-	-	Fault Codes (values separated via ",")		OBD elements	
										FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	
60	Fuel Rate	2	Unsigned	0	32767	0.01	L/h	Engine fuel rate, L/h*100		OBD elements	
										FMBXXX FMB001 FMC001 FMB010 FMB003 FMB110 FMB120 FMB122 FMB125 FMC125 FMC125 FMM125 FMB130 FMC130 FMC130 FMM130 FMB140 FMB150 FMC150 FMM150 FMB900 FMB920 FMB962 FMB964 FM3001 FMT100 MTB100 FMB202 FMB204 FMB206 FMT100 MTB100 FMB140	

## OBD OEM elements

Property ID in AVL packet	Property Name	Bytes	Type	Value range		Multiplier	Units	Description	HW Support	Parameter Group
				Min	Max					
389	OBD OEM Total Mileage	4	Unsigned	0	0xffffffff	-	km	Total mileage received by requesting vehicle specific PID	FMB003	OBD OEM elements
390	OBD OEM Fuel Level	4	Unsigned	0	0xffffffff	0.1	l	Fuel level in litres received by requesting vehicle specific PID	FMB003	OBD OEM elements
402	OEM Distance Until Service	4	Unsigned	0	0xffffffff	-	km	Distance till next service received by requesting vehicle specific PID	FMB001 FMC001 FMM001 FMB003 FMC003 FMM003	OBD OEM elements
410	OEM Battery charge state	1	Unsigned	0	1	-	-	0 - Not charging 1 - Charging	FMB001 FMC001 FMM001 FMB003 FMC003 FMM003	OBD OEM elements
411	OEM Battery charge level	1	Unsigned	0	100	-	%	Represents battery charged level	FMB001 FMC001 FMM001 FMB003 FMC003 FMM003	OBD OEM elements
412	OEM Battery power consumption	2	Unsigned	0	65535	-	kWh/100km	Represents battery power consumption	FMB001 FMC001 FMM001 FMB003 FMC003 FMM003	OBD OEM elements
755	OEM Remaining distance	2	Unsigned	0	65535	-	km	Remaining distance until fuel tank empty or battery (EV) depleted	FMB001 FMC001 FMM001 FMB003 FMC003 FMM003	OBD OEM elements
1151	OEM Battery State Of Health	2	Unsigned	0	65535	-	%	Battery State of Health	FMB001 FMC001 FMM001 FMB003 FMC003 FMM003	OBD OEM elements
1152	OEM Battery Temperature	2	Signed	-32768	32767	-	°C	Battery pack temperature	FMB001 FMC001 FMM001 FMB003 FMC003 FMM003	OBD OEM elements

## BLE Sensors I/O elements

Property ID in AVL packet	Property Name	Bytes	Type	Value range		Multiplier	Units	Description	HW Support	Parameter Group
				Min	Max					

385

Beacon

Variable

HEX

0

1024

-

-

List of Beacon IDs

[FMBX](#)  
[XX](#)  
[FMB0](#)  
[01](#)  
[FMC0](#)  
[01](#)  
[FMB0](#)  
[10](#)  
[FMB0](#)  
[02](#)  
[FMB0](#)  
[20](#)  
[FMB0](#)  
[03](#)  
[FMB1](#)  
[10](#)  
[FMB1](#)  
[20](#)  
[FMB1](#)  
[22](#)  
[FMB1](#)  
[25](#)  
[FMU1](#)  
[25](#)  
[FMC1](#)  
[25](#)  
[FMB1](#)  
[30](#)  
[FMU1](#)  
[30](#)  
[FMC1](#)  
[30](#)  
[FMB1](#)  
[40](#)  
[FMB1](#)  
[50](#)  
[FMC1](#)  
[50](#)  
[FMM](#)  
[150](#)  
[FMB9](#)  
[00](#)  
[FMB9](#)  
[20](#)  
[FMB9](#)  
[10](#)  
[FMB9](#)  
[62](#)  
[FMB9](#)  
[64](#)  
[FM30](#)  
[01](#)  
[FMB2](#)  
[02](#)  
[FMB2](#)  
[04](#)  
[FMB2](#)  
[06](#)  
[FMT1](#)  
[00](#)  
[MTB1](#)  
[00](#)  
[FMP1](#)  
[00](#)  
[FMB1](#)  
[40](#)  
[FMC8](#)  
[00](#)  
[FMM](#)  
[800](#)  
[FMM](#)  
[80A](#)

Permanent I/O elements



										<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	
548	Advanced BLE Beacon data	1024	HEX	0	1024	-	-	List of Beacon Ids and their data when advanced Beacon mode is selected	Eventual I/O elements		

25	BLE Temperature #1	2	Signed	-4000 12500 0.01*	°C	<p>Degrees ( °C ), -40 - +125;  Error codes:  4000 - abnormal sensor state  3000 - sensor not found  2000 - failed sensor data parsing  From firmware version 03.28.00 and up:  32767 - sensor not found  32766 - failed sensor data parsing  32765 - abnormal sensor state</p>	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
----	--------------------	---	--------	-------------------	----	-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

26	BLE Temperature #2	2	Signed	-4000 12500 0.01*	°C	<p>Degrees ( °C ), -40 - +125;  Error codes:  4000 - abnormal sensor state  3000 - sensor not found  2000 - failed sensor data parsing  From firmware version 03.28.00 and up:  32767 - sensor not found  32766 - failed sensor data parsing  32765 - abnormal sensor state</p>	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
----	--------------------	---	--------	-------------------	----	-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

27	BLE Temperature #3	2	Signe d	-4000 12500 0.01* °C	Degrees ( °C ), -40 - +125; Error codes: 4000 - abnormal sensor state 3000 - sensor not found 2000 - failed sensor data parsing From firmware version 03.28.00 and up: 32767 - sensor not found 32766 - failed sensor data parsing 32765 - abnormal sensor state	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
----	--------------------	---	------------	----------------------	------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

28	BLE Temperature #4	2	Signed	-4000 12500 0.01*	°C	<p>Degrees ( °C ), -40 - +125;  Error codes:  4000 - abnormal sensor state  3000 - sensor not found  2000 - failed sensor data parsing  From firmware version 03.28.00 and up:  32767 - sensor not found  32766 - failed sensor data parsing  32765 - abnormal sensor state</p>	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
----	--------------------	---	--------	-------------------	----	-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

29	BLE Battery #1	1	Unsigned	0	100	-	%	Battery level of sensor #1	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
----	----------------	---	----------	---	-----	---	---	----------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

20	BLE Battery #2	1	Unsigned	0	100	-	%	Battery level of sensor #2	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
----	----------------	---	----------	---	-----	---	---	----------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

22	BLE Battery #3	1	Unsigned	0	100	-	%	Battery level of sensor #3	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
----	----------------	---	----------	---	-----	---	---	----------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------



23	BLE Battery #4	1	Unsigned	0	100	-	%	Battery level of sensor #4	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
----	----------------	---	----------	---	-----	---	---	----------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

[FMBX](#)  
[XX](#)  
[FMB0](#)  
[01](#)  
[FMC0](#)  
[01](#)  
[FMB0](#)  
[10](#)  
[FMB0](#)  
[02](#)  
[FMB0](#)  
[20](#)  
[FMB0](#)  
[03](#)  
[FMB1](#)  
[10](#)  
[FMB1](#)  
[20](#)  
[FMB1](#)  
[22](#)  
[FMB1](#)  
[25](#)  
[FMU1](#)  
[25](#)  
[FMC1](#)  
[25](#)  
[FMB1](#)  
[30](#)  
[FMU1](#)  
[30](#)  
[FMC1](#)  
[30](#)  
[FMB1](#)  
[40](#)  
[FMB1](#)  
[50](#)  
[FMC1](#)  
[50](#)  
[FMM](#)  
[150](#)  
[FMB9](#)  
[00](#)  
[FMB9](#)  
[20](#)  
[FMB9](#)  
[10](#)  
[FMB9](#)  
[62](#)  
[FMB9](#)  
[64](#)  
[FM30](#)  
[01](#)  
[FMB2](#)  
[02](#)  
[FMB2](#)  
[04](#)  
[FMB2](#)  
[06](#)  
[FMT1](#)  
[00](#)  
[MTB1](#)  
[00](#)  
[FMP1](#)  
[00](#)  
[FMB1](#)  
[40](#)  
[MSP5](#)  
[00](#)  
[FMC8](#)  
[00](#)  
[FMM](#)  
[800](#)  
[FMM](#)  
[80A](#)

86	BLE Humidity #1	2	Unsig ned	0	1000	0.1*	%RH	<p style="text-align: center;">Humidity</p> <p>From firmware version 03.28.00 and up:  32735 - sensor not found  32734 - failed sensor data parsing  32733 - abnormal sensor state</p>	Bluetooth Low Energy
----	-----------------	---	--------------	---	------	------	-----	----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

104	BLE Humidity #2	2	Unsigned	0	1000	0.1*	%RH	Humidity From firmware version 03.28.00 and up: 32735 - sensor not found 32734 - failed sensor data parsing 32733 - abnormal sensor state	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-----------------	---	----------	---	------	------	-----	-------------------------------------------------------------------------------------------------------------------------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------



108	BLE Humidity #4	2	Unsigned	0	1000	0.1*	%RH	Humidity From firmware version 03.28.00 and up: 32735 - sensor not found 32734 - failed sensor data parsing 32733 - abnormal sensor state	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-----------------	---	----------	---	------	------	-----	-------------------------------------------------------------------------------------------------------------------------------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

270	BLE Fuel Level #1	2	Unsigned	0	65535	-	-	Fuel Level	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-------------------	---	----------	---	-------	---	---	------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

273	BLE Fuel Level #2	2	Unsigned	0	65535	-	-	Fuel Level	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-------------------	---	----------	---	-------	---	---	------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------







									FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	
306	BLE Fuel Frequency #1	4	Unsigned	0	21474 83647	-	-	Frequency value of BLE fuel sensor #1	Bluetooth Low Energy	



											<a href="#">FMBX</a>		
											<a href="#">XX</a>		
											<a href="#">FMB0</a>		
											<a href="#">01</a>		
											<a href="#">FMC0</a>		
											<a href="#">01</a>		
											<a href="#">FMB0</a>		
											<a href="#">10</a>		
											<a href="#">FMB0</a>		
											<a href="#">02</a>		
											<a href="#">FMB0</a>		
											<a href="#">20</a>		
											<a href="#">FMB0</a>		
											<a href="#">03</a>		
											<a href="#">FMB1</a>		
											<a href="#">10</a>		
											<a href="#">FMB1</a>		
											<a href="#">20</a>		
											<a href="#">FMB1</a>		
											<a href="#">22</a>		
											<a href="#">FMB1</a>		
											<a href="#">25</a>		
											<a href="#">FMU1</a>		
											<a href="#">25</a>		
											<a href="#">FMC1</a>		
											<a href="#">25</a>		
											<a href="#">FMB1</a>		
											<a href="#">30</a>		
											<a href="#">FMU1</a>		
											<a href="#">30</a>		
											<a href="#">FMC1</a>		
											<a href="#">30</a>		
											<a href="#">FMB1</a>		
											<a href="#">40</a>		
											<a href="#">FMB1</a>		
											<a href="#">50</a>		
308	BLE Fuel Frequency #3	4	Unsigned	0	21474	-	-	-	-	Frequency value of BLE fuel sensor #3	<a href="#">FMC1</a>	Bluetooth	
			<td>ned</td>	ned		83647						<a href="#">50</a>	Low Energy
											<a href="#">FMM</a>		
											<a href="#">150</a>		
											<a href="#">FMB9</a>		
											<a href="#">00</a>		
											<a href="#">FMB9</a>		
											<a href="#">20</a>		
											<a href="#">FMB9</a>		
											<a href="#">10</a>		
											<a href="#">FMB9</a>		
											<a href="#">62</a>		
											<a href="#">FMB9</a>		
											<a href="#">64</a>		
											<a href="#">FM30</a>		
											<a href="#">01</a>		
											<a href="#">FMB2</a>		
											<a href="#">02</a>		
											<a href="#">FMB2</a>		
											<a href="#">04</a>		
											<a href="#">FMB2</a>		
											<a href="#">06</a>		
											<a href="#">FMT1</a>		
											<a href="#">00</a>		
											<a href="#">MTB1</a>		
											<a href="#">00</a>		
											<a href="#">FMP1</a>		
											<a href="#">00</a>		
											<a href="#">FMB1</a>		
											<a href="#">40</a>		
											<a href="#">MSP5</a>		
											<a href="#">00</a>		
											<a href="#">FMC8</a>		
											<a href="#">00</a>		
											<a href="#">FMM</a>		
											<a href="#">800</a>		
											<a href="#">FMM</a>		
											<a href="#">80A</a>		

FMBX  
XX  
FMB0  
01  
FMC0  
01  
FMB0  
10  
FMB0  
02  
FMB0  
20  
FMB0  
03  
FMB1  
10  
FMB1  
20  
FMB1  
22  
FMB1  
25  
FMU1  
25  
FMC1  
25  
FMB1  
30  
FMU1  
30  
FMC1  
30  
FMB1  
40  
FMB1  
50  
FMC1  
50  
FMM  
150  
FMB9  
00  
FMB9  
20  
FMB9  
10  
FMB9  
62  
FMB9  
64  
FM30  
01  
FMB2  
02  
FMB2  
04  
FMB2  
06  
FMT1  
00  
MTB1  
00  
FMP1  
00  
FMB1  
40  
MSP5  
00  
FMC8  
00  
FMM  
800  
FMM  
80A

309 BLE Fuel Frequency #4 4 Unsigned 0 21474 83647 - - Frequency value of BLE fuel sensor #4

Bluetooth Low Energy

335	BLE Luminosity #1	2	Unsigned	0	0xFF FF	-	lx	Luminosity value of BLE sensor	<a href="#">FMBX XX</a> <a href="#">FMB0 01</a> <a href="#">FMC0 01</a> <a href="#">FMB0 10</a> <a href="#">FMB0 02</a> <a href="#">FMB0 20</a> <a href="#">FMB0 03</a> <a href="#">FMB1 10</a> <a href="#">FMB1 20</a> <a href="#">FMB1 22</a> <a href="#">FMB1 25</a> <a href="#">FMU1 25</a> <a href="#">FMC1 25</a> <a href="#">FMB1 30</a> <a href="#">FMU1 30</a> <a href="#">FMC1 30</a> <a href="#">FMB1 40</a> <a href="#">FMB1 50</a> <a href="#">FMC1 50</a> <a href="#">FMM 150</a> <a href="#">FMB9 00</a> <a href="#">FMB9 20</a> <a href="#">FMB9 10</a> <a href="#">FMB9 62</a> <a href="#">FMB9 64</a> <a href="#">FM30 01</a> <a href="#">FMB2 02</a> <a href="#">FMB2 04</a> <a href="#">FMB2 06</a> <a href="#">FMT1 00</a> <a href="#">MTB1 00</a> <a href="#">FMP1 00</a> <a href="#">FMB1 40</a> <a href="#">MSP5 00</a> <a href="#">FMC8 00</a> <a href="#">FMM 800</a> <a href="#">FMM 80A</a>	Bluetooth Low Energy
-----	-------------------	---	----------	---	------------	---	----	--------------------------------	-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

											<a href="#">FMBX</a>	
											<a href="#">XX</a>	
											<a href="#">FMB0</a>	
											<a href="#">01</a>	
											<a href="#">FMC0</a>	
											<a href="#">01</a>	
											<a href="#">FMB0</a>	
											<a href="#">10</a>	
											<a href="#">FMB0</a>	
											<a href="#">02</a>	
											<a href="#">FMB0</a>	
											<a href="#">20</a>	
											<a href="#">FMB0</a>	
											<a href="#">03</a>	
											<a href="#">FMB1</a>	
											<a href="#">10</a>	
											<a href="#">FMB1</a>	
											<a href="#">20</a>	
											<a href="#">FMB1</a>	
											<a href="#">22</a>	
											<a href="#">FMB1</a>	
											<a href="#">25</a>	
											<a href="#">FMU1</a>	
											<a href="#">25</a>	
											<a href="#">FMC1</a>	
											<a href="#">25</a>	
											<a href="#">FMB1</a>	
											<a href="#">30</a>	
											<a href="#">FMU1</a>	
											<a href="#">30</a>	
											<a href="#">FMC1</a>	
											<a href="#">30</a>	
											<a href="#">FMB1</a>	
											<a href="#">40</a>	
											<a href="#">FMB1</a>	
											<a href="#">50</a>	
336	BLE Luminosity #2	2	Unsigned	0	0xFF	-	lx	Luminosity value of BLE sensor			<a href="#">FMC1</a>	Bluetooth
			ned		FF						<a href="#">50</a>	Low Energy
											<a href="#">FMM</a>	
											<a href="#">150</a>	
											<a href="#">FMB9</a>	
											<a href="#">00</a>	
											<a href="#">FMB9</a>	
											<a href="#">20</a>	
											<a href="#">FMB9</a>	
											<a href="#">10</a>	
											<a href="#">FMB9</a>	
											<a href="#">62</a>	
											<a href="#">FMB9</a>	
											<a href="#">64</a>	
											<a href="#">FM30</a>	
											<a href="#">01</a>	
											<a href="#">FMB2</a>	
											<a href="#">02</a>	
											<a href="#">FMB2</a>	
											<a href="#">04</a>	
											<a href="#">FMB2</a>	
											<a href="#">06</a>	
											<a href="#">FMT1</a>	
											<a href="#">00</a>	
											<a href="#">MTB1</a>	
											<a href="#">00</a>	
											<a href="#">FMP1</a>	
											<a href="#">00</a>	
											<a href="#">FMB1</a>	
											<a href="#">40</a>	
											<a href="#">MSP5</a>	
											<a href="#">00</a>	
											<a href="#">FMC8</a>	
											<a href="#">00</a>	
											<a href="#">FMM</a>	
											<a href="#">800</a>	
											<a href="#">FMM</a>	
											<a href="#">80A</a>	

										FMBX XX	
										<a href="#">FMB0</a>	
										<a href="#">01</a>	
										<a href="#">FMC0</a>	
										<a href="#">01</a>	
										<a href="#">FMB0</a>	
										<a href="#">10</a>	
										<a href="#">FMB0</a>	
										<a href="#">02</a>	
										<a href="#">FMB0</a>	
										<a href="#">20</a>	
										<a href="#">FMB0</a>	
										<a href="#">03</a>	
										<a href="#">FMB1</a>	
										<a href="#">10</a>	
										<a href="#">FMB1</a>	
										<a href="#">20</a>	
										<a href="#">FMB1</a>	
										<a href="#">22</a>	
										<a href="#">FMB1</a>	
										<a href="#">25</a>	
										<a href="#">FMU1</a>	
										<a href="#">25</a>	
										<a href="#">FMC1</a>	
										<a href="#">25</a>	
										<a href="#">FMB1</a>	
										<a href="#">30</a>	
										<a href="#">FMU1</a>	
										<a href="#">30</a>	
										<a href="#">FMC1</a>	
										<a href="#">30</a>	
										<a href="#">FMB1</a>	
										<a href="#">40</a>	
										<a href="#">FMB1</a>	
										<a href="#">50</a>	
337	BLE Luminosity #3	2	Unsigned	0	0xFF	-	lx	Luminosity value of BLE sensor		<a href="#">FMC1</a>	Bluetooth
			ned		FF					<a href="#">50</a>	Low Energy
										<a href="#">FMM</a>	
										<a href="#">150</a>	
										<a href="#">FMB9</a>	
										<a href="#">00</a>	
										<a href="#">FMB9</a>	
										<a href="#">20</a>	
										<a href="#">FMB9</a>	
										<a href="#">10</a>	
										<a href="#">FMB9</a>	
										<a href="#">62</a>	
										<a href="#">FMB9</a>	
										<a href="#">64</a>	
										<a href="#">FM30</a>	
										<a href="#">01</a>	
										<a href="#">FMB2</a>	
										<a href="#">02</a>	
										<a href="#">FMB2</a>	
										<a href="#">04</a>	
										<a href="#">FMB2</a>	
										<a href="#">06</a>	
										<a href="#">FMT1</a>	
										<a href="#">00</a>	
										<a href="#">MTB1</a>	
										<a href="#">00</a>	
										<a href="#">FMP1</a>	
										<a href="#">00</a>	
										<a href="#">FMB1</a>	
										<a href="#">40</a>	
										<a href="#">MSP5</a>	
										<a href="#">00</a>	
										<a href="#">FMC8</a>	
										<a href="#">00</a>	
										<a href="#">FMM</a>	
										<a href="#">800</a>	
										<a href="#">FMM</a>	
										<a href="#">80A</a>	



[FMBX](#)  
[XX](#)  
[FMB0](#)  
[01](#)  
[FMC0](#)  
[01](#)  
[FMB0](#)  
[10](#)  
[FMB0](#)  
[02](#)  
[FMB0](#)  
[20](#)  
[FMB0](#)  
[03](#)  
[FMB1](#)  
[10](#)  
[FMB1](#)  
[20](#)  
[FMB1](#)  
[22](#)  
[FMB1](#)  
[25](#)  
[FMU1](#)  
[25](#)  
[FMC1](#)  
[25](#)  
[FMB1](#)  
[30](#)  
[FMU1](#)  
[30](#)  
[FMC1](#)  
[30](#)  
[FMB1](#)  
[40](#)  
[FMB1](#)  
[50](#)  
[FMC1](#)  
[50](#)  
[FMM](#)  
[150](#)  
[FMB9](#)  
[00](#)  
[FMB9](#)  
[20](#)  
[FMB9](#)  
[10](#)  
[FMB9](#)  
[62](#)  
[FMB9](#)  
[64](#)  
[FM30](#)  
[01](#)  
[FMB2](#)  
[02](#)  
[FMB2](#)  
[04](#)  
[FMB2](#)  
[06](#)  
[FMT1](#)  
[00](#)  
[MTB1](#)  
[00](#)  
[FMP1](#)  
[00](#)  
[FMB1](#)  
[40](#)  
[MSP5](#)  
[00](#)  
[FMC8](#)  
[00](#)  
[FMM](#)  
[800](#)  
[FMM](#)  
[80A](#)

338 BLE Luminosity #4 2 Unsigned 0 0xFF FF - lx Luminosity value of BLE sensor

Bluetooth  
Low Energy

									FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	
331	BLE 1 Custom #1	Variable	HEX	0	-	-	-	Custom IO element for BLE sensor	FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy

463	BLE 1 Custom #2	4	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

464	BLE 1 Custom #3	4	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

465	BLE 1 Custom #4	4	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

466	BLE 1 Custom #5	4	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

									FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	
332	BLE 2 Custom #1	Variable	HEX	0	-	-	-	Custom IO element for BLE sensor	Bluetooth Low Energy	

467	BLE 2 Custom #2	4	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------



468	BLE 2 Custom #3	4	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

469	BLE 2 Custom #4	4	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

470	BLE 2 Custom #5	4	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

									FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	
333	BLE 3 Custom #1	Variable	HEX	0	-	-	-	Custom IO element for BLE sensor	FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	Bluetooth Low Energy

471	BLE 3 Custom #2	4	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------



473	BLE 3 Custom #4	4	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

474	BLE 3 Custom #5	4	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------



										FMBX XX FMB0 01 FMC0 01 FMB0 10 FMB0 02 FMB0 20 FMB0 03 FMB1 10 FMB1 20 FMB1 22 FMB1 25 FMU1 25 FMC1 25 FMB1 30 FMU1 30 FMC1 30 FMB1 40 FMB1 50 FMC1 50 FMM 150 FMB9 00 FMB9 20 FMB9 10 FMB9 62 FMB9 64 FM30 01 FMB2 02 FMB2 04 FMB2 06 FMT1 00 MTB1 00 FMP1 00 FMB1 40 MSP5 00 FMC8 00 FMM 800 FMM 80A	
334	BLE 4 Custom #1	Variable	HEX	0	-	-	-	Custom IO element for BLE sensor		Bluetooth Low Energy	

475	BLE 4 Custom #2	4	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------



477	BLE 4 Custom #4	4	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

478	BLE 4 Custom #5	4	UNSI GNED LONG INT	0	42949 67295	-	-	Custom IO element for BLE sensor	<a href="#">FMBX</a> <a href="#">XX</a> <a href="#">FMB0</a> <a href="#">01</a> <a href="#">FMC0</a> <a href="#">01</a> <a href="#">FMB0</a> <a href="#">10</a> <a href="#">FMB0</a> <a href="#">02</a> <a href="#">FMB0</a> <a href="#">20</a> <a href="#">FMB0</a> <a href="#">03</a> <a href="#">FMB1</a> <a href="#">10</a> <a href="#">FMB1</a> <a href="#">20</a> <a href="#">FMB1</a> <a href="#">22</a> <a href="#">FMB1</a> <a href="#">25</a> <a href="#">FMU1</a> <a href="#">25</a> <a href="#">FMC1</a> <a href="#">25</a> <a href="#">FMB1</a> <a href="#">30</a> <a href="#">FMU1</a> <a href="#">30</a> <a href="#">FMC1</a> <a href="#">30</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">FMB1</a> <a href="#">50</a> <a href="#">FMC1</a> <a href="#">50</a> <a href="#">FMM</a> <a href="#">150</a> <a href="#">FMB9</a> <a href="#">00</a> <a href="#">FMB9</a> <a href="#">20</a> <a href="#">FMB9</a> <a href="#">10</a> <a href="#">FMB9</a> <a href="#">62</a> <a href="#">FMB9</a> <a href="#">64</a> <a href="#">FM30</a> <a href="#">01</a> <a href="#">FMB2</a> <a href="#">02</a> <a href="#">FMB2</a> <a href="#">04</a> <a href="#">FMB2</a> <a href="#">06</a> <a href="#">FMT1</a> <a href="#">00</a> <a href="#">MTB1</a> <a href="#">00</a> <a href="#">FMP1</a> <a href="#">00</a> <a href="#">FMB1</a> <a href="#">40</a> <a href="#">MSP5</a> <a href="#">00</a> <a href="#">FMC8</a> <a href="#">00</a> <a href="#">FMM</a> <a href="#">800</a> <a href="#">FMM</a> <a href="#">80A</a>	Bluetooth Low Energy
-----	-----------------	---	-----------------------------	---	----------------	---	---	----------------------------------	--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	-------------------------

# CAN adapters elements

Property ID in AVE packet	Property Name	Bytes	Type	Value range		Multiplier	Units	Description	HW Support	Parameter Group
				Min	Max					
81	Vehicle Speed	1	Unsigned	0	255	-	km/h	Vehicle Speed	LUCAN200, ALLCANS00, CANCONTROL	
										FMXXXX [261110]
										251129
										251130
										251131
										251132
										251133
										251134
										251135
										251136
										251137
										251138
										251139
										251140
										251141
										82
FMXXXX [261110]										
251129										
251130										
251131										
251132										
251133										
251134										
251135										
251136										
251137										
251138										
251139										
251140										
251141										
83	Fuel Consumed	4	Unsigned	0	2147483647	0.1	l	Value in liters	LUCAN200, ALLCANS00, CANCONTROL	
										FMXXXX [261110]
										251129
										251130
										251131
										251132
										251133
										251134
										251135
										251136
										251137
										251138
										251139
										251140
										251141
										84
FMXXXX [261110]										
251129										
251130										
251131										
251132										
251133										
251134										
251135										
251136										
251137										
251138										
251139										
251140										
251141										
85	Engine RPM	2	Unsigned	0	16384	-	rpm	Value in rounds per minute	LUCAN200, ALLCANS00, CANCONTROL	
										FMXXXX [261110]
										251129
										251130
										251131
										251132
										251133
										251134
										251135
										251136
										251137
										251138
										251139
										251140
										251141
										87
FMXXXX [261110]										
251129										
251130										
251131										
251132										
251133										
251134										
251135										
251136										
251137										
251138										
251139										
251140										
251141										
89	Fuel level	1	Unsigned	0	100	-	%	Value in percentages	LUCAN200, ALLCANS00, CANCONTROL	
										FMXXXX [261110]
										251129
										251130
										251131
										251132
										251133
										251134
										251135
										251136
										251137
										251138
										251139
										251140
										251141
										90
FMXXXX [261110]										
251129										
251130										
251131										
251132										
251133										
251134										
251135										
251136										
251137										
251138										
251139										
251140										
251141										
100	Program Number	4	Unsigned	0	99999	-	-	Value: Min = 0, Max = 99999	LUCAN200, ALLCANS00, CANCONTROL	
										FMXXXX [261110]
										251129
										251130
										251131
										251132
										251133
										251134
										251135
										251136
										251137
										251138
										251139
										251140
										251141
										101
FMXXXX [261110]										
251129										
251130										
251131										
251132										
251133										
251134										
251135										
251136										
251137										
251138										
251139										
251140										
251141										
108	Module ID 17b	17	HEX	0	0a7fffffff	-	-	Module ID 17 bytes	LUCAN200, ALLCANS00, CANCONTROL	
										FMXXXX [261110]
										251129
										251130
										251131
										251132
										251133
										251134
										251135
										251136
										251137
										251138
										251139
										251140
										251141
										102
FMXXXX [261110]										
251129										
251130										
251131										
251132										
251133										
251134										
251135										
251136										
251137										
251138										
251139										
251140										
251141										
103	Engine Worktime (rounded)	4	Unsigned	0	1677215	-	min	Total engine work time	ALLCANS00, CANCONTROL	
										FMXXXX [261110]
										251129
										251130
										251131
										251132
										251133
										251134
										251135
										251136
										251137
										251138
										251139
										251140
										251141
										105
FMXXXX [261110]										
251129										
251130										
251131										
251132										
251133										
251134										
251135										
251136										
251137										
251138										
251139										
251140										
251141										
107	Fuel Consumed (rounded)	4	Unsigned	0	2147483647	0.1	l	Total Fuel Consumed	LUCAN200, ALLCANS00, CANCONTROL	
										FMXXXX [261110]
										251129
										251130
										251131
										251132
										251133
										251134
										251135
										251136
										251137
										251138
										251139
										251140
										251141
										110
FMXXXX [261110]										
251129										
251130										
251131										
251132										
251133										
251134										
251135										
251136										
251137										
251138										
251139										
251140										
251141										
111	AdBlue Level	1	Unsigned	0	100	-	%	AdBlue	ALLCANS00	
										FMXXXX [261110]
										251129
										251130
										251131
										251132
										251133
										251134
										251135
										251136
										251137
										251138
										251139
										251140
										251141

ID	Parameter Name	Units	Min	Max	Resolution	Scale	Offset	Physical Unit	Control Type
112	AdBlue Level	2	Unassigned	0	6535	0.1	l	AdBlue level	ALLCAN300
114	Engine Load	1	Unassigned	0	130	-	%	Engine Load	ALLCAN300
115	Engine Temperature	2	Signal	400	1270	0.1	°C	Engine Temperature	LUCAN200, ALLCAN300, CANCONTROL
118	Axle 1 Load	2	Unassigned	0	32768	-	kg	Axle 1 load	ALLCAN300
119	Axle 2 Load	2	Unassigned	0	32768	-	kg	Axle 2 load	ALLCAN300
120	Axle 3 Load	2	Unassigned	0	32768	-	kg	Axle 3 load	ALLCAN300
121	Axle 4 Load	2	Unassigned	0	32768	-	kg	Axle 4 load	ALLCAN300
122	Axle 5 Load	2	Unassigned	0	32768	-	kg	Axle 5 load	ALLCAN300
123	Control State Flags	4	Unassigned	0	4294967295	-	-	Control state flags	ALLCAN300, CANCONTROL
124	Agricultural Machinery Flags	8	Unassigned	0	0xFFFFFFFF	-	-	Agricultural machinery flags	ALLCAN300
125	Harvesting Time	4	Unassigned	0	16777215	-	min	Harvesting time	ALLCAN300
126	Area of Harvest	4	Unassigned	0	4294967295	-	m²	Area of harvest in square meters	ALLCAN300
127	Mowing Efficiency	4	Unassigned	0	4294967295	-	m³/h	Mowing efficiency	ALLCAN300
128	Grain Mow Volume	4	Unassigned	0	4294967295	-	kg	Mow volume	ALLCAN300
129	Grain Moisture	2	Unassigned	0	100	-	%	Grain moisture	ALLCAN300
130	Harvesting Drum RPM	2	Unassigned	0	6535	-	rpm	Harvesting drum rpm	ALLCAN300
131	Gap Under Harvesting Drum	1	Unassigned	0	255	-	mm	Gap under harvesting drum	ALLCAN300
132	Security State Flags	8	Unassigned	0	0xFFFFFFFF	-	-	Security state flags	ALLCAN300, CANCONTROL

133	Tachograph Total Vehicle Distance	4	Unsigned	0	4294987295	-	m	Tachog Total Vehicle Distance	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
134	Trip Distance	4	Unsigned	0	4294987295	-	m	Trip distance	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
135	Tachograph Vehicle Speed	2	Unsigned	0	255	-	km/h	Tachog vehicle speed	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
136	Tachog Driver Card Presence	1	Unsigned	0	3	-	-	Tachog Driver Card Presence	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
137	Driver 1 Status	1	Unsigned	0	255	-	-	Driver 1 Status	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
138	Driver 2 Status	1	Unsigned	0	255	-	-	Driver 2 Status	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
139	Driver 1 Continuous Driving Time	2	Unsigned	0	65535	-	min.	Driver 1 Continuous Driving Time, minutes	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
140	Driver 2 Continuous Driving Time	2	Unsigned	0	65535	-	min.	Driver 2 Continuous Driving Time, minutes	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
141	Driver 1 Cumulative Break Time	2	Unsigned	0	65535	-	min.	Driver 1 Cumulative Break Time, minutes	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
142	Driver 2 Cumulative Break Time	2	Unsigned	0	65535	-	min.	Driver 2 Cumulative Break Time, minutes	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
143	Driver 1 Selected Activity Duration	2	Unsigned	0	65535	-	min.	Driver 1 Duration Of Selected Activity, minutes	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
144	Driver 2 Selected Activity Duration	2	Unsigned	0	65535	-	min.	Driver 2 Duration Of Selected Activity, minutes	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
145	Driver 1 Cumulative Driving Time	2	Unsigned	0	65535	-	min.	Driver 1 Cumulative Driving Time, minutes	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
146	Driver 2 Cumulative Driving Time	2	Unsigned	0	65535	-	min.	Driver 2 Cumulative Driving Time, minutes	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
147	Driver 1 ID High	8	Unsigned	0	0aFFFFFFFFFFFFFF	-	-	Driver 1 ID High	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
148	Driver 1 ID Low	8	Unsigned	0	0aFFFFFFFFFFFFFF	-	-	Driver 1 ID Low	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
149	Driver 2 ID High	8	Unsigned	0	0aFFFFFFFFFFFFFF	-	-	Driver 2 ID High	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
150	Driver 2 ID Low	8	Unsigned	0	0aFFFFFFFFFFFFFF	-	-	Driver 2 ID Low	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
151	Battery Temperature	2	Signed	-600	1270	0.1	°C	Battery temperature in Celsius	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
152	BV Battery Level	1	Unsigned	0	100	-	%	Battery level in percent	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300, CANCONTROL
160	DTC Faults	1	Unsigned	0	255	-	-	DTC faults Count	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300, CANCONTROL
161	Slope of Arm	2	Signed	-3276	3276	-	Degrees °	Slope Of Arm	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
162	Rotation of Arm	2	Signed	-180	180	-	Degrees °	Rotation Of Arm	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300
163	Eject of Arm	2	Unsigned	0	6553	-	m	Eject of arm	FM8XXX 04a0110 04a0111 04a0112 04a0113 04a0114 04a0115 04a0116 04a0117 04a0118 04a0119 04a0120	ALLCAN300



144	Horizontal Distance Arm Vehicle	2	Unassigned	0	6553	-	m	Horizontal Distance Arm Vehicle	<a href="#">FM8XX 246116</a> <a href="#">246117</a> <a href="#">246118</a> <a href="#">246119</a> <a href="#">246120</a> <a href="#">246121</a> <a href="#">246122</a> <a href="#">246123</a> <a href="#">246124</a> <a href="#">246125</a> <a href="#">246126</a> <a href="#">246127</a> <a href="#">246128</a> <a href="#">246129</a> <a href="#">246130</a>	ALLCAND30
145	Height Arm Above Ground	2	Unassigned	0	6553	-	m	Height Arm Above Ground	<a href="#">FM8XX 246131</a> <a href="#">246132</a> <a href="#">246133</a> <a href="#">246134</a> <a href="#">246135</a> <a href="#">246136</a> <a href="#">246137</a> <a href="#">246138</a> <a href="#">246139</a> <a href="#">246140</a>	ALLCAND30
146	Roll RPM	2	Unassigned	0	65535	-	rpm	Roll RPM	<a href="#">FM8XX 246141</a> <a href="#">246142</a> <a href="#">246143</a> <a href="#">246144</a> <a href="#">246145</a> <a href="#">246146</a> <a href="#">246147</a> <a href="#">246148</a> <a href="#">246149</a> <a href="#">246150</a>	ALLCAND30
147	Amount Of Spread Salt Square Meter	2	Unassigned	0	655	-	g/m <sup>2</sup>	Amount Of Spread Salt Square Meter	<a href="#">FM8XX 246151</a> <a href="#">246152</a> <a href="#">246153</a> <a href="#">246154</a> <a href="#">246155</a> <a href="#">246156</a> <a href="#">246157</a> <a href="#">246158</a> <a href="#">246159</a> <a href="#">246160</a>	ALLCAND30
148	Battery Voltage	2	Unassigned	0	6553	-	V	Battery Voltage	<a href="#">FM8XX 246161</a> <a href="#">246162</a> <a href="#">246163</a> <a href="#">246164</a> <a href="#">246165</a> <a href="#">246166</a> <a href="#">246167</a> <a href="#">246168</a> <a href="#">246169</a> <a href="#">246170</a>	ALLCAND30
149	Amount Of Spread Fine Grained Salt	4	Unassigned	0	167722	-	T	Amount Of Spread Fine Grained Salt	<a href="#">FM8XX 246171</a> <a href="#">246172</a> <a href="#">246173</a> <a href="#">246174</a> <a href="#">246175</a> <a href="#">246176</a> <a href="#">246177</a> <a href="#">246178</a> <a href="#">246179</a> <a href="#">246180</a>	ALLCAND30
170	Amount Of Coarse Grained Salt	4	Unassigned	0	167722	-	T	Amount Of Coarse Grained Salt	<a href="#">FM8XX 246181</a> <a href="#">246182</a> <a href="#">246183</a> <a href="#">246184</a> <a href="#">246185</a> <a href="#">246186</a> <a href="#">246187</a> <a href="#">246188</a> <a href="#">246189</a> <a href="#">246190</a>	ALLCAND30
171	Amount Of Spread DMs	4	Unassigned	0	167722	-	T	Amount Of Spread DMs	<a href="#">FM8XX 246191</a> <a href="#">246192</a> <a href="#">246193</a> <a href="#">246194</a> <a href="#">246195</a> <a href="#">246196</a> <a href="#">246197</a> <a href="#">246198</a> <a href="#">246199</a> <a href="#">246200</a>	ALLCAND30
172	Amount Of Spread Coarse Grained Calcium	4	Unassigned	0	167722	-	m <sup>3</sup>	Amount Of Spread Coarse Grained Calcium	<a href="#">FM8XX 246201</a> <a href="#">246202</a> <a href="#">246203</a> <a href="#">246204</a> <a href="#">246205</a> <a href="#">246206</a> <a href="#">246207</a> <a href="#">246208</a> <a href="#">246209</a> <a href="#">246210</a>	ALLCAND30
173	Amount Of Spread Calcium Chloride	4	Unassigned	0	167722	-	m <sup>3</sup>	Amount Of Spread Calcium Chloride	<a href="#">FM8XX 246211</a> <a href="#">246212</a> <a href="#">246213</a> <a href="#">246214</a> <a href="#">246215</a> <a href="#">246216</a> <a href="#">246217</a> <a href="#">246218</a> <a href="#">246219</a> <a href="#">246220</a>	ALLCAND30
174	Amount Of Spread Sodium Chloride	4	Unassigned	0	167722	-	m <sup>3</sup>	Amount Of Spread Sodium Chloride	<a href="#">FM8XX 246221</a> <a href="#">246222</a> <a href="#">246223</a> <a href="#">246224</a> <a href="#">246225</a> <a href="#">246226</a> <a href="#">246227</a> <a href="#">246228</a> <a href="#">246229</a> <a href="#">246230</a>	ALLCAND30
176	Amount Of Spread Magnesium Chloride	4	Unassigned	0	167722	-	m <sup>3</sup>	Amount Of Spread Magnesium Chloride	<a href="#">FM8XX 246231</a> <a href="#">246232</a> <a href="#">246233</a> <a href="#">246234</a> <a href="#">246235</a> <a href="#">246236</a> <a href="#">246237</a> <a href="#">246238</a> <a href="#">246239</a> <a href="#">246240</a>	ALLCAND30
177	Amount Of Spread Gravel	4	Unassigned	0	167722	-	T	Amount Of Spread Gravel	<a href="#">FM8XX 246241</a> <a href="#">246242</a> <a href="#">246243</a> <a href="#">246244</a> <a href="#">246245</a> <a href="#">246246</a> <a href="#">246247</a> <a href="#">246248</a> <a href="#">246249</a> <a href="#">246250</a>	ALLCAND30
178	Amount Of Spread Sand	4	Unassigned	0	167722	-	T	Amount Of Spread Sand	<a href="#">FM8XX 246251</a> <a href="#">246252</a> <a href="#">246253</a> <a href="#">246254</a> <a href="#">246255</a> <a href="#">246256</a> <a href="#">246257</a> <a href="#">246258</a> <a href="#">246259</a> <a href="#">246260</a>	ALLCAND30
183	Width Peering Left	2	Unassigned	0	655	-	m	Width Peering Left	<a href="#">FM8XX 246261</a> <a href="#">246262</a> <a href="#">246263</a> <a href="#">246264</a> <a href="#">246265</a> <a href="#">246266</a> <a href="#">246267</a> <a href="#">246268</a> <a href="#">246269</a> <a href="#">246270</a>	ALLCAND30
184	Width Peering Right	2	Unassigned	0	655	-	m	Width Peering Right	<a href="#">FM8XX 246271</a> <a href="#">246272</a> <a href="#">246273</a> <a href="#">246274</a> <a href="#">246275</a> <a href="#">246276</a> <a href="#">246277</a> <a href="#">246278</a> <a href="#">246279</a> <a href="#">246280</a>	ALLCAND30
185	Salt Spreader Working Hours	4	Unassigned	0	167722	-	h	Salt Spreader Working Hours	<a href="#">FM8XX 246281</a> <a href="#">246282</a> <a href="#">246283</a> <a href="#">246284</a> <a href="#">246285</a> <a href="#">246286</a> <a href="#">246287</a> <a href="#">246288</a> <a href="#">246289</a> <a href="#">246290</a>	ALLCAND30
186	Distance During Salting	4	Unassigned	0	167722	-	km	Distance During Salting	<a href="#">FM8XX 246291</a> <a href="#">246292</a> <a href="#">246293</a> <a href="#">246294</a> <a href="#">246295</a> <a href="#">246296</a> <a href="#">246297</a> <a href="#">246298</a> <a href="#">246299</a> <a href="#">246300</a>	ALLCAND30
187	Load Weight	4	Unassigned	0	16772215	-	kg	Load Weight	<a href="#">FM8XX 246301</a> <a href="#">246302</a> <a href="#">246303</a> <a href="#">246304</a> <a href="#">246305</a> <a href="#">246306</a> <a href="#">246307</a> <a href="#">246308</a> <a href="#">246309</a> <a href="#">246310</a>	ALLCAND30
188	Retarder Load	1	Unassigned	0	130	-	%	Retarder Load in percent	<a href="#">FM8XX 246311</a> <a href="#">246312</a> <a href="#">246313</a> <a href="#">246314</a> <a href="#">246315</a> <a href="#">246316</a> <a href="#">246317</a> <a href="#">246318</a> <a href="#">246319</a> <a href="#">246320</a>	ALLCAND30
189	Cruise Time	4	Unassigned	0	16772215	-	min	Cruise time in minutes	<a href="#">FM8XX 246321</a> <a href="#">246322</a> <a href="#">246323</a> <a href="#">246324</a> <a href="#">246325</a> <a href="#">246326</a> <a href="#">246327</a> <a href="#">246328</a> <a href="#">246329</a> <a href="#">246330</a>	ALLCAND30
232	CNG Status	1	Unassigned	0	1	-	-	CNG Status	<a href="#">FM8XX 246331</a> <a href="#">246332</a> <a href="#">246333</a> <a href="#">246334</a> <a href="#">246335</a> <a href="#">246336</a> <a href="#">246337</a> <a href="#">246338</a> <a href="#">246339</a> <a href="#">246340</a>	LUCAND30, CANCONTROL
233	CNG Used	4	Unassigned	0	16772215	-	kg	CNG used	<a href="#">FM8XX 246341</a> <a href="#">246342</a> <a href="#">246343</a> <a href="#">246344</a> <a href="#">246345</a> <a href="#">246346</a> <a href="#">246347</a> <a href="#">246348</a> <a href="#">246349</a> <a href="#">246350</a>	LUCAND30, CANCONTROL



454	SSF Front Left Door Open	1	Unassigned	0	1	-	-	0 - Closed 1 - Open	<a href="#">FMHXX 126116</a> <a href="#">126117</a> <a href="#">126118</a> <a href="#">126119</a> <a href="#">126120</a> <a href="#">126121</a> <a href="#">126122</a> <a href="#">126123</a> <a href="#">126124</a> <a href="#">126125</a> <a href="#">126126</a> <a href="#">126127</a> <a href="#">126128</a> <a href="#">126129</a> <a href="#">126130</a>	LVGAN, ALLGAND00, CANCONTROL
455	SSF Front Right Door Open	1	Unassigned	0	1	-	-	0 - Closed 1 - Open	<a href="#">FMHXX 126131</a> <a href="#">126132</a> <a href="#">126133</a> <a href="#">126134</a> <a href="#">126135</a> <a href="#">126136</a> <a href="#">126137</a> <a href="#">126138</a> <a href="#">126139</a> <a href="#">126140</a> <a href="#">126141</a> <a href="#">126142</a> <a href="#">126143</a> <a href="#">126144</a> <a href="#">126145</a> <a href="#">126146</a> <a href="#">126147</a> <a href="#">126148</a> <a href="#">126149</a> <a href="#">126150</a>	LVGAN, ALLGAND00, CANCONTROL
456	SSF Rear Left Door Open	1	Unassigned	0	1	-	-	0 - Closed 1 - Open	<a href="#">FMHXX 126151</a> <a href="#">126152</a> <a href="#">126153</a> <a href="#">126154</a> <a href="#">126155</a> <a href="#">126156</a> <a href="#">126157</a> <a href="#">126158</a> <a href="#">126159</a> <a href="#">126160</a> <a href="#">126161</a> <a href="#">126162</a> <a href="#">126163</a> <a href="#">126164</a> <a href="#">126165</a> <a href="#">126166</a> <a href="#">126167</a> <a href="#">126168</a> <a href="#">126169</a> <a href="#">126170</a>	LVGAN, ALLGAND00, CANCONTROL
457	SSF Rear Right Door Open	1	Unassigned	0	1	-	-	0 - Closed 1 - Open	<a href="#">FMHXX 126171</a> <a href="#">126172</a> <a href="#">126173</a> <a href="#">126174</a> <a href="#">126175</a> <a href="#">126176</a> <a href="#">126177</a> <a href="#">126178</a> <a href="#">126179</a> <a href="#">126180</a> <a href="#">126181</a> <a href="#">126182</a> <a href="#">126183</a> <a href="#">126184</a> <a href="#">126185</a> <a href="#">126186</a> <a href="#">126187</a> <a href="#">126188</a> <a href="#">126189</a> <a href="#">126190</a>	LVGAN, ALLGAND00, CANCONTROL
458	SSF Trunk Door Open	1	Unassigned	0	1	-	-	0 - Closed 1 - Open	<a href="#">FMHXX 126191</a> <a href="#">126192</a> <a href="#">126193</a> <a href="#">126194</a> <a href="#">126195</a> <a href="#">126196</a> <a href="#">126197</a> <a href="#">126198</a> <a href="#">126199</a> <a href="#">126200</a> <a href="#">126201</a> <a href="#">126202</a> <a href="#">126203</a> <a href="#">126204</a> <a href="#">126205</a> <a href="#">126206</a> <a href="#">126207</a> <a href="#">126208</a> <a href="#">126209</a> <a href="#">126210</a>	LVGAN, ALLGAND00, CANCONTROL
913	SSF Engine Cover Open	1	Unassigned	0	1	-	-	0 - Closed 1 - Open	<a href="#">FMHXX 126211</a> <a href="#">126212</a> <a href="#">126213</a> <a href="#">126214</a> <a href="#">126215</a> <a href="#">126216</a> <a href="#">126217</a> <a href="#">126218</a> <a href="#">126219</a> <a href="#">126220</a> <a href="#">126221</a> <a href="#">126222</a> <a href="#">126223</a> <a href="#">126224</a> <a href="#">126225</a> <a href="#">126226</a> <a href="#">126227</a> <a href="#">126228</a> <a href="#">126229</a> <a href="#">126230</a>	LVGAN, ALLGAND00, CANCONTROL
909	SSF Roof Open	1	Unassigned	0	1	-	-	0 - Closed 1 - Open	<a href="#">FMHXX 126231</a> <a href="#">126232</a> <a href="#">126233</a> <a href="#">126234</a> <a href="#">126235</a> <a href="#">126236</a> <a href="#">126237</a> <a href="#">126238</a> <a href="#">126239</a> <a href="#">126240</a> <a href="#">126241</a> <a href="#">126242</a> <a href="#">126243</a> <a href="#">126244</a> <a href="#">126245</a> <a href="#">126246</a> <a href="#">126247</a> <a href="#">126248</a> <a href="#">126249</a> <a href="#">126250</a>	LVGAN, ALLGAND00, CANCONTROL
914	SSF Charging Wire Plugged	1	Unassigned	0	1	-	-	0 - Unplugged 1 - Plugged	<a href="#">FMHXX 126251</a> <a href="#">126252</a> <a href="#">126253</a> <a href="#">126254</a> <a href="#">126255</a> <a href="#">126256</a> <a href="#">126257</a> <a href="#">126258</a> <a href="#">126259</a> <a href="#">126260</a> <a href="#">126261</a> <a href="#">126262</a> <a href="#">126263</a> <a href="#">126264</a> <a href="#">126265</a> <a href="#">126266</a> <a href="#">126267</a> <a href="#">126268</a> <a href="#">126269</a> <a href="#">126270</a>	ALLGAND00, CANCONTROL
915	SSF Battery Charging	1	Unassigned	0	1	-	-	0 - Not charging 1 - Charging	<a href="#">FMHXX 126271</a> <a href="#">126272</a> <a href="#">126273</a> <a href="#">126274</a> <a href="#">126275</a> <a href="#">126276</a> <a href="#">126277</a> <a href="#">126278</a> <a href="#">126279</a> <a href="#">126280</a> <a href="#">126281</a> <a href="#">126282</a> <a href="#">126283</a> <a href="#">126284</a> <a href="#">126285</a> <a href="#">126286</a> <a href="#">126287</a> <a href="#">126288</a> <a href="#">126289</a> <a href="#">126290</a>	ALLGAND00, CANCONTROL
916	SSF Electric Engine State	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FMHXX 126291</a> <a href="#">126292</a> <a href="#">126293</a> <a href="#">126294</a> <a href="#">126295</a> <a href="#">126296</a> <a href="#">126297</a> <a href="#">126298</a> <a href="#">126299</a> <a href="#">126300</a> <a href="#">126301</a> <a href="#">126302</a> <a href="#">126303</a> <a href="#">126304</a> <a href="#">126305</a> <a href="#">126306</a> <a href="#">126307</a> <a href="#">126308</a> <a href="#">126309</a> <a href="#">126310</a>	ALLGAND00, CANCONTROL
917	SSF Car Closed Factory Remote	1	Unassigned	0	1	-	-	0 - Closed 1 - Open	<a href="#">FMHXX 126311</a> <a href="#">126312</a> <a href="#">126313</a> <a href="#">126314</a> <a href="#">126315</a> <a href="#">126316</a> <a href="#">126317</a> <a href="#">126318</a> <a href="#">126319</a> <a href="#">126320</a> <a href="#">126321</a> <a href="#">126322</a> <a href="#">126323</a> <a href="#">126324</a> <a href="#">126325</a> <a href="#">126326</a> <a href="#">126327</a> <a href="#">126328</a> <a href="#">126329</a> <a href="#">126330</a>	ALLGAND00, CANCONTROL
922	SSF Car Is Closed	1	Unassigned	0	1	-	-	0 - Closed 1 - Open	<a href="#">FMHXX 126331</a> <a href="#">126332</a> <a href="#">126333</a> <a href="#">126334</a> <a href="#">126335</a> <a href="#">126336</a> <a href="#">126337</a> <a href="#">126338</a> <a href="#">126339</a> <a href="#">126340</a> <a href="#">126341</a> <a href="#">126342</a> <a href="#">126343</a> <a href="#">126344</a> <a href="#">126345</a> <a href="#">126346</a> <a href="#">126347</a> <a href="#">126348</a> <a href="#">126349</a> <a href="#">126350</a>	ALLGAND00, CANCONTROL
918	SSF Factory Alarm Actuated	1	Unassigned	0	1	-	-	0 - Not actuated 1 - Actuated	<a href="#">FMHXX 126351</a> <a href="#">126352</a> <a href="#">126353</a> <a href="#">126354</a> <a href="#">126355</a> <a href="#">126356</a> <a href="#">126357</a> <a href="#">126358</a> <a href="#">126359</a> <a href="#">126360</a> <a href="#">126361</a> <a href="#">126362</a> <a href="#">126363</a> <a href="#">126364</a> <a href="#">126365</a> <a href="#">126366</a> <a href="#">126367</a> <a href="#">126368</a> <a href="#">126369</a> <a href="#">126370</a>	ALLGAND00, CANCONTROL
919	SSF Factory Alarm Enabled	1	Unassigned	0	1	-	-	0 - Not enabled 1 - Enabled	<a href="#">FMHXX 126371</a> <a href="#">126372</a> <a href="#">126373</a> <a href="#">126374</a> <a href="#">126375</a> <a href="#">126376</a> <a href="#">126377</a> <a href="#">126378</a> <a href="#">126379</a> <a href="#">126380</a> <a href="#">126381</a> <a href="#">126382</a> <a href="#">126383</a> <a href="#">126384</a> <a href="#">126385</a> <a href="#">126386</a> <a href="#">126387</a> <a href="#">126388</a> <a href="#">126389</a> <a href="#">126390</a>	ALLGAND00, CANCONTROL
920	SSF Signal Close Factory Remote	1	Unassigned	0	1	-	-	0 - Closed 1 - Open	<a href="#">FMHXX 126391</a> <a href="#">126392</a> <a href="#">126393</a> <a href="#">126394</a> <a href="#">126395</a> <a href="#">126396</a> <a href="#">126397</a> <a href="#">126398</a> <a href="#">126399</a> <a href="#">126400</a> <a href="#">126401</a> <a href="#">126402</a> <a href="#">126403</a> <a href="#">126404</a> <a href="#">126405</a> <a href="#">126406</a> <a href="#">126407</a> <a href="#">126408</a> <a href="#">126409</a> <a href="#">126410</a>	ALLGAND00, CANCONTROL
921	SSF Signal Open Factory Remote	1	Unassigned	0	1	-	-	0 - Closed 1 - Open	<a href="#">FMHXX 126411</a> <a href="#">126412</a> <a href="#">126413</a> <a href="#">126414</a> <a href="#">126415</a> <a href="#">126416</a> <a href="#">126417</a> <a href="#">126418</a> <a href="#">126419</a> <a href="#">126420</a> <a href="#">126421</a> <a href="#">126422</a> <a href="#">126423</a> <a href="#">126424</a> <a href="#">126425</a> <a href="#">126426</a> <a href="#">126427</a> <a href="#">126428</a> <a href="#">126429</a> <a href="#">126430</a>	ALLGAND00, CANCONTROL
922	SSF Rearming Signal	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FMHXX 126431</a> <a href="#">126432</a> <a href="#">126433</a> <a href="#">126434</a> <a href="#">126435</a> <a href="#">126436</a> <a href="#">126437</a> <a href="#">126438</a> <a href="#">126439</a> <a href="#">126440</a> <a href="#">126441</a> <a href="#">126442</a> <a href="#">126443</a> <a href="#">126444</a> <a href="#">126445</a> <a href="#">126446</a> <a href="#">126447</a> <a href="#">126448</a> <a href="#">126449</a> <a href="#">126450</a>	ALLGAND00, CANCONTROL
923	SSF Trunk Door Opened Factory Remote	1	Unassigned	0	1	-	-	0 - Closed 1 - Open	<a href="#">FMHXX 126451</a> <a href="#">126452</a> <a href="#">126453</a> <a href="#">126454</a> <a href="#">126455</a> <a href="#">126456</a> <a href="#">126457</a> <a href="#">126458</a> <a href="#">126459</a> <a href="#">126460</a> <a href="#">126461</a> <a href="#">126462</a> <a href="#">126463</a> <a href="#">126464</a> <a href="#">126465</a> <a href="#">126466</a> <a href="#">126467</a> <a href="#">126468</a> <a href="#">126469</a> <a href="#">126470</a>	ALLGAND00, CANCONTROL
924	SSF CAN Module Is Sleep	1	Unassigned	0	1	-	-	0 - Not in sleep 1 - In sleep	<a href="#">FMHXX 126471</a> <a href="#">126472</a> <a href="#">126473</a> <a href="#">126474</a> <a href="#">126475</a> <a href="#">126476</a> <a href="#">126477</a> <a href="#">126478</a> <a href="#">126479</a> <a href="#">126480</a> <a href="#">126481</a> <a href="#">126482</a> <a href="#">126483</a> <a href="#">126484</a> <a href="#">126485</a> <a href="#">126486</a> <a href="#">126487</a> <a href="#">126488</a> <a href="#">126489</a> <a href="#">126490</a>	LVGAN, ALLGAND00, CANCONTROL
925	SSF Factory Remote 3s	1	Unassigned	0	1	-	-	0 - No 1 - Yes	<a href="#">FMHXX 126491</a> <a href="#">126492</a> <a href="#">126493</a> <a href="#">126494</a> <a href="#">126495</a> <a href="#">126496</a> <a href="#">126497</a> <a href="#">126498</a> <a href="#">126499</a> <a href="#">126500</a> <a href="#">126501</a> <a href="#">126502</a> <a href="#">126503</a> <a href="#">126504</a> <a href="#">126505</a> <a href="#">126506</a> <a href="#">126507</a> <a href="#">126508</a> <a href="#">126509</a> <a href="#">126510</a>	ALLGAND00
926	SSF Factory Armed	1	Unassigned	0	1	-	-	0 - Not armed 1 - Armed	<a href="#">FMHXX 126511</a> <a href="#">126512</a> <a href="#">126513</a> <a href="#">126514</a> <a href="#">126515</a> <a href="#">126516</a> <a href="#">126517</a> <a href="#">126518</a> <a href="#">126519</a> <a href="#">126520</a> <a href="#">126521</a> <a href="#">126522</a> <a href="#">126523</a> <a href="#">126524</a> <a href="#">126525</a> <a href="#">126526</a> <a href="#">126527</a> <a href="#">126528</a> <a href="#">126529</a> <a href="#">126530</a>	CANCONTROL
960	SSF Parking Gear Active (automatic gear box)	1	Unassigned	0	1	-	-	0 - Inactive 1 - Active	<a href="#">FMHXX 126531</a> <a href="#">126532</a> <a href="#">126533</a> <a href="#">126534</a> <a href="#">126535</a> <a href="#">126536</a> <a href="#">126537</a> <a href="#">126538</a> <a href="#">126539</a> <a href="#">126540</a> <a href="#">126541</a> <a href="#">126542</a> <a href="#">126543</a> <a href="#">126544</a> <a href="#">126545</a> <a href="#">126546</a> <a href="#">126547</a> <a href="#">126548</a> <a href="#">126549</a> <a href="#">126550</a>	ALLGAND00, CANCONTROL
961	SSF Reverse Gear Active	1	Unassigned	0	1	-	-	0 - Inactive 1 - Active	<a href="#">FMHXX 126551</a> <a href="#">126552</a> <a href="#">126553</a> <a href="#">126554</a> <a href="#">126555</a> <a href="#">126556</a> <a href="#">126557</a> <a href="#">126558</a> <a href="#">126559</a> <a href="#">126560</a> <a href="#">126561</a> <a href="#">126562</a> <a href="#">126563</a> <a href="#">126564</a> <a href="#">126565</a> <a href="#">126566</a> <a href="#">126567</a> <a href="#">126568</a> <a href="#">126569</a> <a href="#">126570</a>	ALLGAND00, CANCONTROL
959	SSF Neutral Gear Active (automatic gear box)	1	Unassigned	0	1	-	-	0 - Inactive 1 - Active	<a href="#">FMHXX 126571</a> <a href="#">126572</a> <a href="#">126573</a> <a href="#">126574</a> <a href="#">126575</a> <a href="#">126576</a> <a href="#">126577</a> <a href="#">126578</a> <a href="#">126579</a> <a href="#">126580</a> <a href="#">126581</a> <a href="#">126582</a> <a href="#">126583</a> <a href="#">126584</a> <a href="#">126585</a> <a href="#">126586</a> <a href="#">126587</a> <a href="#">126588</a> <a href="#">126589</a> <a href="#">126590</a>	ALLGAND00, CANCONTROL













1094	ASF Section 5 Spraying	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126110</a> <a href="#">126111</a> <a href="#">126112</a> <a href="#">126113</a> <a href="#">126114</a> <a href="#">126115</a> <a href="#">126116</a> <a href="#">126117</a> <a href="#">126118</a> <a href="#">126119</a> <a href="#">126120</a>	ALLCAND30
1095	ASF Section 6 Spraying	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126121</a> <a href="#">126122</a> <a href="#">126123</a> <a href="#">126124</a> <a href="#">126125</a> <a href="#">126126</a> <a href="#">126127</a> <a href="#">126128</a> <a href="#">126129</a> <a href="#">126130</a>	ALLCAND30
1096	ASF Section 7 Spraying	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126131</a> <a href="#">126132</a> <a href="#">126133</a> <a href="#">126134</a> <a href="#">126135</a> <a href="#">126136</a> <a href="#">126137</a> <a href="#">126138</a> <a href="#">126139</a> <a href="#">126140</a>	ALLCAND30
1097	ASF Section 8 Spraying	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126141</a> <a href="#">126142</a> <a href="#">126143</a> <a href="#">126144</a> <a href="#">126145</a> <a href="#">126146</a> <a href="#">126147</a> <a href="#">126148</a> <a href="#">126149</a> <a href="#">126150</a>	ALLCAND30
1098	ASF Section 9 Spraying	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126151</a> <a href="#">126152</a> <a href="#">126153</a> <a href="#">126154</a> <a href="#">126155</a> <a href="#">126156</a> <a href="#">126157</a> <a href="#">126158</a> <a href="#">126159</a> <a href="#">126160</a>	ALLCAND30
1036	USF Spreading	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126161</a> <a href="#">126162</a> <a href="#">126163</a> <a href="#">126164</a> <a href="#">126165</a> <a href="#">126166</a> <a href="#">126167</a> <a href="#">126168</a> <a href="#">126169</a> <a href="#">126170</a>	ALLCAND30
1037	USF Picking Chemicals	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126171</a> <a href="#">126172</a> <a href="#">126173</a> <a href="#">126174</a> <a href="#">126175</a> <a href="#">126176</a> <a href="#">126177</a> <a href="#">126178</a> <a href="#">126179</a> <a href="#">126180</a>	ALLCAND30
1038	USF Conveyor Belt	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126181</a> <a href="#">126182</a> <a href="#">126183</a> <a href="#">126184</a> <a href="#">126185</a> <a href="#">126186</a> <a href="#">126187</a> <a href="#">126188</a> <a href="#">126189</a> <a href="#">126190</a>	ALLCAND30
1039	USF Salt Spreader's Drive Wheel	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126191</a> <a href="#">126192</a> <a href="#">126193</a> <a href="#">126194</a> <a href="#">126195</a> <a href="#">126196</a> <a href="#">126197</a> <a href="#">126198</a> <a href="#">126199</a> <a href="#">126200</a>	ALLCAND30
1040	USF Brushes	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126201</a> <a href="#">126202</a> <a href="#">126203</a> <a href="#">126204</a> <a href="#">126205</a> <a href="#">126206</a> <a href="#">126207</a> <a href="#">126208</a> <a href="#">126209</a> <a href="#">126210</a>	ALLCAND30
1041	USF Vacuum Cleaner	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126211</a> <a href="#">126212</a> <a href="#">126213</a> <a href="#">126214</a> <a href="#">126215</a> <a href="#">126216</a> <a href="#">126217</a> <a href="#">126218</a> <a href="#">126219</a> <a href="#">126220</a>	ALLCAND30
1042	USF Water Supply	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126221</a> <a href="#">126222</a> <a href="#">126223</a> <a href="#">126224</a> <a href="#">126225</a> <a href="#">126226</a> <a href="#">126227</a> <a href="#">126228</a> <a href="#">126229</a> <a href="#">126230</a>	ALLCAND30
1043	USF Spreading	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126231</a> <a href="#">126232</a> <a href="#">126233</a> <a href="#">126234</a> <a href="#">126235</a> <a href="#">126236</a> <a href="#">126237</a> <a href="#">126238</a> <a href="#">126239</a> <a href="#">126240</a>	ALLCAND30
1044	USF Liquid pump	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126241</a> <a href="#">126242</a> <a href="#">126243</a> <a href="#">126244</a> <a href="#">126245</a> <a href="#">126246</a> <a href="#">126247</a> <a href="#">126248</a> <a href="#">126249</a> <a href="#">126250</a>	ALLCAND30
1045	USF Unloading From The Hopper	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126251</a> <a href="#">126252</a> <a href="#">126253</a> <a href="#">126254</a> <a href="#">126255</a> <a href="#">126256</a> <a href="#">126257</a> <a href="#">126258</a> <a href="#">126259</a> <a href="#">126260</a>	ALLCAND30
1046	USF Low Salt (Sand) Level In Container Indicator	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126261</a> <a href="#">126262</a> <a href="#">126263</a> <a href="#">126264</a> <a href="#">126265</a> <a href="#">126266</a> <a href="#">126267</a> <a href="#">126268</a> <a href="#">126269</a> <a href="#">126270</a>	ALLCAND30
1047	USF Low Water Level In Container Indicator	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126271</a> <a href="#">126272</a> <a href="#">126273</a> <a href="#">126274</a> <a href="#">126275</a> <a href="#">126276</a> <a href="#">126277</a> <a href="#">126278</a> <a href="#">126279</a> <a href="#">126280</a>	ALLCAND30
1048	USF Chemicals	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126281</a> <a href="#">126282</a> <a href="#">126283</a> <a href="#">126284</a> <a href="#">126285</a> <a href="#">126286</a> <a href="#">126287</a> <a href="#">126288</a> <a href="#">126289</a> <a href="#">126290</a>	ALLCAND30
1049	USF Compressor	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126291</a> <a href="#">126292</a> <a href="#">126293</a> <a href="#">126294</a> <a href="#">126295</a> <a href="#">126296</a> <a href="#">126297</a> <a href="#">126298</a> <a href="#">126299</a> <a href="#">126300</a>	ALLCAND30
1050	USF Water Valve Is Opened	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126301</a> <a href="#">126302</a> <a href="#">126303</a> <a href="#">126304</a> <a href="#">126305</a> <a href="#">126306</a> <a href="#">126307</a> <a href="#">126308</a> <a href="#">126309</a> <a href="#">126310</a>	ALLCAND30
1051	USF Cabin Moved Up Status Active	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126311</a> <a href="#">126312</a> <a href="#">126313</a> <a href="#">126314</a> <a href="#">126315</a> <a href="#">126316</a> <a href="#">126317</a> <a href="#">126318</a> <a href="#">126319</a> <a href="#">126320</a>	ALLCAND30
1052	USF Cabin Moved Down Status Active	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126321</a> <a href="#">126322</a> <a href="#">126323</a> <a href="#">126324</a> <a href="#">126325</a> <a href="#">126326</a> <a href="#">126327</a> <a href="#">126328</a> <a href="#">126329</a> <a href="#">126330</a>	ALLCAND30
1099	USF Hydraulic Work Not Permitted	1	Unassigned	0	1	-	-	0 - Off 1 - On	<a href="#">FM8XX 126331</a> <a href="#">126332</a> <a href="#">126333</a> <a href="#">126334</a> <a href="#">126335</a> <a href="#">126336</a> <a href="#">126337</a> <a href="#">126338</a> <a href="#">126339</a> <a href="#">126340</a>	ALLCAND30
1053	OSF Section 1 Presence Of Fluid In The Downpipe	1	Unassigned	0	1	-	-	0 - No presence 1 - Present	<a href="#">FM8XX 126341</a> <a href="#">126342</a> <a href="#">126343</a> <a href="#">126344</a> <a href="#">126345</a> <a href="#">126346</a> <a href="#">126347</a> <a href="#">126348</a> <a href="#">126349</a> <a href="#">126350</a>	ALLCAND30

1054	CSP Section 1 Filled	1	Unassigned	0	1	-	-	0 - No 1 - Yes	FM8XX 204110 204111 204112 204113 204114 204115 204116 204117 204118 204119 204120 204121 204122 204123 204124 204125 204126 204127 204128 204129 204130	ALLCAND30
1055	CSP Section 1 Overfilled	1	Unassigned	0	1	-	-	0 - No 1 - Yes	FM8XX 204131 204132 204133 204134 204135 204136 204137 204138 204139 204140 204141 204142 204143 204144 204145 204146 204147 204148 204149 204150	ALLCAND30
1056	CSP Section 2 Presence Of Fluid In The Downpipe	1	Unassigned	0	1	-	-	0 - No presence 1 - Present	FM8XX 204151 204152 204153 204154 204155 204156 204157 204158 204159 204160 204161 204162 204163 204164 204165 204166 204167 204168 204169 204170	ALLCAND30
1057	CSP Section 2 Filled	1	Unassigned	0	1	-	-	0 - No 1 - Yes	FM8XX 204171 204172 204173 204174 204175 204176 204177 204178 204179 204180 204181 204182 204183 204184 204185 204186 204187 204188 204189 204190	ALLCAND30
1058	CSP Section 2 Overfilled	1	Unassigned	0	1	-	-	0 - No 1 - Yes	FM8XX 204191 204192 204193 204194 204195 204196 204197 204198 204199 204200 204201 204202 204203 204204 204205 204206 204207 204208 204209 204210	ALLCAND30
1059	CSP Section 3 Presence Of Fluid In The Downpipe	1	Unassigned	0	1	-	-	0 - No presence 1 - Present	FM8XX 204211 204212 204213 204214 204215 204216 204217 204218 204219 204220 204221 204222 204223 204224 204225 204226 204227 204228 204229 204230	ALLCAND30
1060	CSP Section 3 Filled	1	Unassigned	0	1	-	-	0 - No 1 - Yes	FM8XX 204231 204232 204233 204234 204235 204236 204237 204238 204239 204240 204241 204242 204243 204244 204245 204246 204247 204248 204249 204250	ALLCAND30
1061	CSP Section 3 Overfilled	1	Unassigned	0	1	-	-	0 - No 1 - Yes	FM8XX 204251 204252 204253 204254 204255 204256 204257 204258 204259 204260 204261 204262 204263 204264 204265 204266 204267 204268 204269 204270	ALLCAND30
1062	CSP Section 4 Presence Of Fluid In The Downpipe	1	Unassigned	0	1	-	-	0 - No presence 1 - Present	FM8XX 204271 204272 204273 204274 204275 204276 204277 204278 204279 204280 204281 204282 204283 204284 204285 204286 204287 204288 204289 204290	ALLCAND30
1063	CSP Section 4 Filled	1	Unassigned	0	1	-	-	0 - No 1 - Yes	FM8XX 204291 204292 204293 204294 204295 204296 204297 204298 204299 204300 204301 204302 204303 204304 204305 204306 204307 204308 204309 204310	ALLCAND30
1064	CSP Section 4 Overfilled	1	Unassigned	0	1	-	-	0 - No 1 - Yes	FM8XX 204311 204312 204313 204314 204315 204316 204317 204318 204319 204320 204321 204322 204323 204324 204325 204326 204327 204328 204329 204330	ALLCAND30
1065	CSP Section 5 Presence Of Fluid In The Downpipe	1	Unassigned	0	1	-	-	0 - No presence 1 - Present	FM8XX 204331 204332 204333 204334 204335 204336 204337 204338 204339 204340 204341 204342 204343 204344 204345 204346 204347 204348 204349 204350	ALLCAND30
1066	CSP Section 5 Filled	1	Unassigned	0	1	-	-	0 - No 1 - Yes	FM8XX 204351 204352 204353 204354 204355 204356 204357 204358 204359 204360 204361 204362 204363 204364 204365 204366 204367 204368 204369 204370	ALLCAND30
1067	CSP Section 5 Overfilled	1	Unassigned	0	1	-	-	0 - No 1 - Yes	FM8XX 204371 204372 204373 204374 204375 204376 204377 204378 204379 204380 204381 204382 204383 204384 204385 204386 204387 204388 204389 204390	ALLCAND30
1068	CSP Section 6 Presence Of Fluid In The Downpipe	1	Unassigned	0	1	-	-	0 - No presence 1 - Present	FM8XX 204391 204392 204393 204394 204395 204396 204397 204398 204399 204400 204401 204402 204403 204404 204405 204406 204407 204408 204409 204410	ALLCAND30
1069	CSP Section 6 Filled	1	Unassigned	0	1	-	-	0 - No 1 - Yes	FM8XX 204411 204412 204413 204414 204415 204416 204417 204418 204419 204420 204421 204422 204423 204424 204425 204426 204427 204428 204429 204430	ALLCAND30
1070	CSP Section 6 Overfilled	1	Unassigned	0	1	-	-	0 - No 1 - Yes	FM8XX 204431 204432 204433 204434 204435 204436 204437 204438 204439 204440 204441 204442 204443 204444 204445 204446 204447 204448 204449 204450	ALLCAND30
1071	CSP Section 7 Presence Of Fluid In The Downpipe	1	Unassigned	0	1	-	-	0 - No presence 1 - Present	FM8XX 204451 204452 204453 204454 204455 204456 204457 204458 204459 204460 204461 204462 204463 204464 204465 204466 204467 204468 204469 204470	ALLCAND30
1072	CSP Section 7 Filled	1	Unassigned	0	1	-	-	0 - No 1 - Yes	FM8XX 204471 204472 204473 204474 204475 204476 204477 204478 204479 204480 204481 204482 204483 204484 204485 204486 204487 204488 204489 204490	ALLCAND30
1073	CSP Section 7 Overfilled	1	Unassigned	0	1	-	-	0 - No 1 - Yes	FM8XX 204491 204492 204493 204494 204495 204496 204497 204498 204499 204500 204501 204502 204503 204504 204505 204506 204507 204508 204509 204510	ALLCAND30
1074	CSP Section 8 Presence Of Fluid In The Downpipe	1	Unassigned	0	1	-	-	0 - No presence 1 - Present	FM8XX 204511 204512 204513 204514 204515 204516 204517 204518 204519 204520 204521 204522 204523 204524 204525 204526 204527 204528 204529 204530	ALLCAND30
1075	CSP Section 8 Filled	1	Unassigned	0	1	-	-	0 - No 1 - Yes	FM8XX 204531 204532 204533 204534 204535 204536 204537 204538 204539 204540 204541 204542 204543 204544 204545 204546 204547 204548 204549 204550	ALLCAND30
1076	CSP Section 8 Overfilled	1	Unassigned	0	1	-	-	0 - No 1 - Yes	FM8XX 204551 204552 204553 204554 204555 204556 204557 204558 204559 204560 204561 204562 204563 204564 204565 204566 204567 204568 204569 204570	ALLCAND30
400	Distance to Next Service	4	Unassigned	0	4294907295	-	-		FM8XX 204571 204572 204573 204574 204575 204576 204577 204578 204579 204580 204581 204582 204583 204584 204585 204586 204587 204588 204589 204590	CAN adapters

450	CNG Level Kg	2	Unassigned	0	65335	10	Kg	CNG Level Kg (appears only if CNG level percentage is not available)	<a href="#">FMISXX 1262116</a> <a href="#">1262117</a> <a href="#">1262118</a> <a href="#">1262119</a> <a href="#">1262120</a> <a href="#">1262121</a> <a href="#">1262122</a> <a href="#">1262123</a> <a href="#">1262124</a> <a href="#">1262125</a> <a href="#">1262126</a> <a href="#">1262127</a> <a href="#">1262128</a> <a href="#">1262129</a> <a href="#">1262130</a>	CAN adapters
459	Distance from need of service	4	Unassigned	0	4294967295	-	km	Service - distance elapsed since the occurrence of the need for servicing	<a href="#">FMISXX 1262131</a> <a href="#">1262132</a> <a href="#">1262133</a> <a href="#">1262134</a> <a href="#">1262135</a> <a href="#">1262136</a> <a href="#">1262137</a> <a href="#">1262138</a> <a href="#">1262139</a> <a href="#">1262140</a>	CAN adapters
460	Distance from last service	4	Unassigned	0	4294967295	-	km	Service - distance from the last service	<a href="#">FMISXX 1262141</a> <a href="#">1262142</a> <a href="#">1262143</a> <a href="#">1262144</a> <a href="#">1262145</a> <a href="#">1262146</a> <a href="#">1262147</a> <a href="#">1262148</a> <a href="#">1262149</a> <a href="#">1262150</a>	CAN adapters
461	Time to next service	2	Unassigned	0	65335	-	day	Service - time to next service	<a href="#">FMISXX 1262151</a> <a href="#">1262152</a> <a href="#">1262153</a> <a href="#">1262154</a> <a href="#">1262155</a> <a href="#">1262156</a> <a href="#">1262157</a> <a href="#">1262158</a> <a href="#">1262159</a> <a href="#">1262160</a>	CAN adapters
462	Time from need of service	2	Unassigned	0	65335	-	day	Service - time exceeded since the occurrence of the need for servicing	<a href="#">FMISXX 1262161</a> <a href="#">1262162</a> <a href="#">1262163</a> <a href="#">1262164</a> <a href="#">1262165</a> <a href="#">1262166</a> <a href="#">1262167</a> <a href="#">1262168</a> <a href="#">1262169</a> <a href="#">1262170</a>	CAN adapters
463	Time from last service	2	Unassigned	0	65335	-	day	Service - time elapsed since the last service	<a href="#">FMISXX 1262171</a> <a href="#">1262172</a> <a href="#">1262173</a> <a href="#">1262174</a> <a href="#">1262175</a> <a href="#">1262176</a> <a href="#">1262177</a> <a href="#">1262178</a> <a href="#">1262179</a> <a href="#">1262180</a>	CAN adapters
464	Distance to next oil service	4	Unassigned	0	4294967295	-	km	Service - distance to next oil service	<a href="#">FMISXX 1262181</a> <a href="#">1262182</a> <a href="#">1262183</a> <a href="#">1262184</a> <a href="#">1262185</a> <a href="#">1262186</a> <a href="#">1262187</a> <a href="#">1262188</a> <a href="#">1262189</a> <a href="#">1262190</a>	CAN adapters
465	Time to next oil service	2	Unassigned	0	65335	-	day	Service - time to next oil service	<a href="#">FMISXX 1262191</a> <a href="#">1262192</a> <a href="#">1262193</a> <a href="#">1262194</a> <a href="#">1262195</a> <a href="#">1262196</a> <a href="#">1262197</a> <a href="#">1262198</a> <a href="#">1262199</a> <a href="#">1262200</a>	CAN adapters
466	LVCAN Vehicle Range	4	Unassigned	0	4294967295	-	km	Information about vehicle range	<a href="#">FMISXX 1262201</a> <a href="#">1262202</a> <a href="#">1262203</a> <a href="#">1262204</a> <a href="#">1262205</a> <a href="#">1262206</a> <a href="#">1262207</a> <a href="#">1262208</a> <a href="#">1262209</a> <a href="#">1262210</a>	CAN adapters
467	LVCAN Total CNG coated	4	Unassigned	0	65335	-	kg	Information about Total CNG used in coated mode	<a href="#">FMISXX 1262211</a> <a href="#">1262212</a> <a href="#">1262213</a> <a href="#">1262214</a> <a href="#">1262215</a> <a href="#">1262216</a> <a href="#">1262217</a> <a href="#">1262218</a> <a href="#">1262219</a> <a href="#">1262220</a>	CAN adapters
1079	Total Bale Count	4	Unassigned	0	04FFFFFFF	-	-	Total Bale Count	<a href="#">FMISXX 1262221</a> <a href="#">1262222</a> <a href="#">1262223</a> <a href="#">1262224</a> <a href="#">1262225</a> <a href="#">1262226</a> <a href="#">1262227</a> <a href="#">1262228</a> <a href="#">1262229</a> <a href="#">1262230</a>	CAN adapters
1080	Bale Count	4	Unassigned	0	04FFFFFFF	-	-	Bale Count	<a href="#">FMISXX 1262231</a> <a href="#">1262232</a> <a href="#">1262233</a> <a href="#">1262234</a> <a href="#">1262235</a> <a href="#">1262236</a> <a href="#">1262237</a> <a href="#">1262238</a> <a href="#">1262239</a> <a href="#">1262240</a>	CAN adapters
1081	Cut Bale Count	4	Unassigned	0	04FFFFFFF	-	-	Cut Bale Count	<a href="#">FMISXX 1262241</a> <a href="#">1262242</a> <a href="#">1262243</a> <a href="#">1262244</a> <a href="#">1262245</a> <a href="#">1262246</a> <a href="#">1262247</a> <a href="#">1262248</a> <a href="#">1262249</a> <a href="#">1262250</a>	CAN adapters
1082	Bale Slices	4	Unassigned	0	04FFFFFFF	-	-	Bale Slices	<a href="#">FMISXX 1262251</a> <a href="#">1262252</a> <a href="#">1262253</a> <a href="#">1262254</a> <a href="#">1262255</a> <a href="#">1262256</a> <a href="#">1262257</a> <a href="#">1262258</a> <a href="#">1262259</a> <a href="#">1262260</a>	CAN adapters
1116	LVCAN MaxRoadSpeed	1	Unassigned	0	255	-	km/h	Maximum speed from road signs	<a href="#">FMISXX 1262261</a> <a href="#">1262262</a> <a href="#">1262263</a> <a href="#">1262264</a> <a href="#">1262265</a> <a href="#">1262266</a> <a href="#">1262267</a> <a href="#">1262268</a> <a href="#">1262269</a> <a href="#">1262270</a>	CAN adapters
1117	LVCAN ExceededRoadSpeed	1	Unassigned	0	255	-	km/h	Exceeded speed from road signs	<a href="#">FMISXX 1262271</a> <a href="#">1262272</a> <a href="#">1262273</a> <a href="#">1262274</a> <a href="#">1262275</a> <a href="#">1262276</a> <a href="#">1262277</a> <a href="#">1262278</a> <a href="#">1262279</a> <a href="#">1262280</a>	CAN adapters
1205	LVCAN RSP SpeedLimitSign	1	Unassigned	0	1	-	-	Information of road sign "Speed limit with value" is recognized/cancelled	<a href="#">FMISXX 1262281</a> <a href="#">1262282</a> <a href="#">1262283</a> <a href="#">1262284</a> <a href="#">1262285</a> <a href="#">1262286</a> <a href="#">1262287</a> <a href="#">1262288</a> <a href="#">1262289</a> <a href="#">1262290</a>	CAN adapters
1206	LVCAN RSP EndOfSpeedLimitSign	1	Unassigned	0	1	-	-	Information of road sign "End of speed limit with value" is recognized/cancelled	<a href="#">FMISXX 1262291</a> <a href="#">1262292</a> <a href="#">1262293</a> <a href="#">1262294</a> <a href="#">1262295</a> <a href="#">1262296</a> <a href="#">1262297</a> <a href="#">1262298</a> <a href="#">1262299</a> <a href="#">1262300</a>	CAN adapters
1207	LVCAN RSP SpeedExceeded	1	Unassigned	0	1	-	-	Information if speed is exceeded indicated by road sign "Speed limit with value"	<a href="#">FMISXX 1262301</a> <a href="#">1262302</a> <a href="#">1262303</a> <a href="#">1262304</a> <a href="#">1262305</a> <a href="#">1262306</a> <a href="#">1262307</a> <a href="#">1262308</a> <a href="#">1262309</a> <a href="#">1262310</a>	CAN adapters
1208	LVCAN RSP TimeOfSpeedLimitSign	1	Unassigned	0	1	-	-	Information of road sign "Conditional time-specific speed limit with value" is recognized/cancelled	<a href="#">FMISXX 1262311</a> <a href="#">1262312</a> <a href="#">1262313</a> <a href="#">1262314</a> <a href="#">1262315</a> <a href="#">1262316</a> <a href="#">1262317</a> <a href="#">1262318</a> <a href="#">1262319</a> <a href="#">1262320</a>	CAN adapters
1209	LVCAN RSP WthrSpeedLimitSign	1	Unassigned	0	1	-	-	Information of road sign "Speed limit with value due to weather conditions" is recognized/cancelled	<a href="#">FMISXX 1262321</a> <a href="#">1262322</a> <a href="#">1262323</a> <a href="#">1262324</a> <a href="#">1262325</a> <a href="#">1262326</a> <a href="#">1262327</a> <a href="#">1262328</a> <a href="#">1262329</a> <a href="#">1262330</a>	CAN adapters