

# B6-24 / B10-24 / BB-WP - FIRE ALARM BELL



## B6-24/B10-24/BB-WP


## APPLICATIONS

The B6-24 and B10-24 provide durable and dependable operation required for life safety alarm systems.

Alarm bells are low current, high decibel notification appliances for use in fire or other signaling applications. The alarm bell is powered by 24VDC.

Alarm bells are available in 6" or 10" version and listed for indoor and outdoor applications. Alarm bells must be used with the BB-WP weatherproof box for outdoor use.

### WIRING DIAGRAM



SPECIFICATION	
Model	B6-24, B10-24
Operating Voltage	24VDC
Alarm Current	100mA
dB at 10ft.	96dB
Operating Temperature	32°F to 120° F
(Indoor Application)	(0° C to 48° C)
Operating Temperature	-32°F to 150° F
(Outdoor Application)	(-35° C to 65° C)
Color / Material	Red / Metal
Back box Dimension	4.25W" x 4.25"H x 1.5"D

# STANDARD FEATURES

- UL Listed
- Available in 6" or 10" version
- High dbA output
- · Mounts to a standard 4" square electrical box
- ANSI/UL Listed for outdoor use when used with the BB-WP weatherproof back box
- 18 AWG wire leads
- Meets ANSI/UL 464 requirements
- · Red metal finish



- UL 464 S1529
- CSFM Listed 7135-0410:0209

#### **Product Compliance**

• NFPA 72

Specifications subject to change without notice.

#### Hochiki America Corporation

7051 Village Drive, Suite 100 Buena Park, CA 90621-2268 Phone: 714/522-2246 Fax: 714/522-2268 Technical Support: 800/845-6692 or technical support@hochiki.com Find latest revision at www.hochiki.com



F0192 10/2014

Continued on back.

# MOUNTING

