

DS-PM1-RT-HWB 433MHz Tri-X Wireless Receiver



Tri-X wireless receiver, compatible with AX Hybrid Pro control panel, used to expand wireless capability of the control panel. HIKVISION Tri-X detectors can be added to AX Hybrid Pro panel via this wireless receiver.

- 433MHz wireless receiver
- Wireless transmission distance up to 1300m
- Supports 32 wireless detectors, 4 wireless indoor sounders and 4 wireless outdoor sounders

▪ Specification

Software features	
Compatibility list	DS-PS1-I-WB DS-PS1-E-WB DS-PM1-O1L-WB DS-PM1-O1H-WB DS-PDP15P-EG2-WB DS-PDC15-EG2-WB DS-PDD12P-EG2-WB DS-PDMC-EG2-WB DS-PDMCS-EG2-WB DS-PDEB1-EG2-WB DS-PDEBP1-EG2-WB DS-PDWL-E-WB DS-PDPG12P-EG2-WB DS-PDMCK-EG2-WB DS-PDTPH-E-WB DS-PDCL12-EG2-WB DS-PDC10AM-EG2-WB DS-PDC10DM-EGW-WB
Hardware features	
Bus	1 Speed-X bus
Electrical characteristics	
Power supply	9 to 24 VDC
Typical voltage	12 VDC
Power consumption	Maximum current: 100 mA@12 VDC Quiescent current: 40 mA@12 VDC
Wireless transmission	
RF frequency	433 MHz
Wireless security	Frequency hopping 128 AES encryption
Display	
LED Indicator	1. Green: power/find me 2. Orange: alarm/fault
General	
Dimension(WxHxD)	110 mm × 155 mm × 32 mm
Shell material	Plastic
Weight	233 g
Operation temperature	-10°C to 40°C
Operation humidity	10% to 90%
Device management	
Alarm input	Up to 32 wireless detectors(portable emergency button is not included)
Wireless sounder	Up to 4 wireless indoor sounder, 4 wireless outdoor sounder



▪ Available Model

DS-PM1-RT-HWB

DS-PM1-RT-HWB/美国Ecom定制

▪ **Accessory**

▪ **Included**

DS-PHA48-EP	DS-PHA64-LP
	

**The Detectors that DS-PM1-RT-HWB Supports*

Headquarters

No.555 Qianmo Road, Binjiang District,
Hangzhou 310051, China
T +86-571-8807-5998
www.hikvision.com



Follow us on social media to get the latest product and solution information.

