



# **T8 LED TUBE**

## **MODEL: LEDT81200ALD**

LED Tube Lighting is the most prevalent light source among

Residential, Industrial and Commercial buildings, perfect fits to any industry.

# **OVERVIEW**

- \* LM80 approved Philips SMD2835 LEDs with lifetime more than 50,000 hours.
- \* High brightness, lumen efficacy up to 120-160Lm/W.
- \* Soft and homogenous light.
- \* Easy installation with fast connection

**PHYSICAL DATA** 

- \* Idea replacement for traditional fluorescent tube.
- \* 3 years warranty, more than 50,000 hours reliable lifespan.
- \* 1.5KV Surge Protection, avoiding damage caused by voltage fluctuation and Lightning Strike.


Dimension	D25.8*1200 mm			
Lamp N.W.	175 g			
LED Chip PCB	Aluminum			
Material	30% Aluminum + 70% PC Cover			
IP Rating	IP20			
Endcap	G13			
ELECTRICAL DATA				
Wattage	18W			
Power Factor	PF>0.95			
Voltage	100-277VAC			
Driver	Flicking			
Input	One-side			
Surge Protection	>1.5KV			

OPTICAL DATA				
Lumen Flux	>2160LM			
Lamp Efficacy	>120Lm/W			
LEDs	Philips SMD2835 (LM80)			
CRI	>80			
ССТ	3000K /4000K /5000K /6500K			
SDCM	<3			
Beam Angle	120 Degree			

600 |1200mm

LIFE DATA & OPERATING DATA				
Lifetime of Lamp	<b>of Lamp</b> >50,000 hours (L70)			
Lumen Maintenance	>95% after 10000 Hours			
Warranty	3 Years			
Working Temperature	-15°C+40°C			
Recommend Install Height	<5M			

# PRODUCT STRUCTURE





### **APPLICATION**


Lighting area like the home lighting, industrial lighting-warehouse, factory, or commercial lighting-supermarket, restaurant



### LIGHT DISTRIBUTION








Remark: Above test data base on 18W 120Lm/W CCT 5000K @AC220V testing environment.

### **INSTALLATION**

- 1. Before installation, power supply must be shut down to ensure safety.
- 2. Do not operate with traditional dimmer, electric switches and remote controls.
- 3. Use only in specified nominal voltage and temperature range.

#### TWO-SIDES POWER SUPPLY TUBE



Wiring with Magnetic Ballast & Starter


Starter


Fluorescent Tube


L

Magnetic Ballast











#### **PACKING**

Size	QTY/CTN	Box Size	CTN Size	N.W./CTN	G.W./CTN
1200 MM	30 PCS	28*28*1219 MM	122.6*19.5*16.5 CM	5.24 KG	7.63 KG


#### **ONE-SIDE POWER SUPPLY TUBE**








Option 1 (Remove the Electronic Ballast)





Option 2 (Remove the Magnetic Ballast and Starter)

