

# **DS-1293ZJ**


## Indoor/Outdoor Wall Mount Bracket



## Features:

- Aluminum alloy material with surface spray treatment
- The bracket has built-in outlet hole
- Camera soleplate has sponge mat
- Camera soleplate is rotatable

#### **Dimension:**



# **Order Model:**

DS-1293ZJ

#### Parameter:


Model	DS-1293ZJ
	Wall Mount Bracket for
Parameters	Box Camera
Appearance	Hikvision White
Application	For box, bullet and zoom camera
Material	Aluminum alloy
Angle adjustment	Pan: 360°, Tilt: -45°∼45°
Dimension	88×116.6×297.3mm
Weight	473g
Accessories	DS-1275ZJ(Vertical Pole mount bracket)


## **Notice:**


- Notice the color of bracket.
- The bracket should be installed on flat wall.
- The diameter of outlet hole must be less than 6.5mm.
- The wall must be capable of supporting over 3 times as much as the total weight of the camera and the mount.
- The maximum load capacity of the bracket is 6KG.

# **Installation Step:**

- ① Choose the proper wall
- $\ensuremath{\textcircled{2}} \ensuremath{ \text{ Complete bracket installation, threading, adjust direction of pedestal}$
- ③ Fix camera on the soleplate









Note: A is tilt adjustment screw, B is pan adjustment screw.

- ④ Wiring, adjust the screws to adjust the camera's direction.
- ⑤ This bracket can be used with housing.





Note: The box dome camera may vary from the picture above.